

EF3000iSE
EF3000iSEB

WARNING

The engine exhaust from this product contains chemicals known to the State of California to cause cancer, birth defects or other reproductive harm.

YAMAHA

LIT-CALIF-65-01

INTRODUCTION

Congratulations on your purchase of your new Yamaha.

This manual will provide you with a good basic understanding of the operation and maintenance of this machine.

If you have any questions regarding the operation or maintenance of your machine, please consult a Yamaha dealer.

PRI-I.D. NUMBER


MODEL	
<input type="text"/>	
PRI-I.D. CODE	SERIAL No.
<input type="text"/>	<input type="text"/>

AE00012

IDENTIFICATION NUMBER RECORDS

Record your Primary I.D., and serial numbers in the spaces provided, to assist you in ordering spare parts from a Yamaha dealer.

Also record and keep these I.D. numbers in a separate place in case your machine is stolen.



AE00011

MACHINE IDENTIFICATION


The machine serial number is stamped in the location as shown.

NOTE: _____

The first three digits of these numbers are for model identification; the remaining digits are the unit production number. Keep a record of these numbers for reference when ordering parts from a Yamaha dealer.

AE00022

EF3000iSE
EF3000iSEB
OWNER'S MANUAL
© 2002 by Yamaha Motor Corporation, U.S.A.
1st Edition, September 2002
All rights reserved.
Any reprinting or unauthorized use
without the written permission of
Yamaha Motor Corporation, U.S.A.
is expressly prohibited.
Printed in Japan.
P/N LIT-19626-01-03



AE00032

⚠ WARNING

PLEASE READ AND UNDERSTAND THIS MANUAL COMPLETELY BEFORE OPERATING THE MACHINE.

Particularly important information is distinguished in this manual by the following notations.



The Safety Alert Symbol means **ATTENTION! BECOME ALERT! YOUR SAFETY IS INVOLVED!**

⚠ WARNING

Failure to follow WARNING instructions could result in severe injury or death to the engine operator, a bystander, or a person inspecting or repairing the engine.

CAUTION:

A CAUTION indicates special precautions that must be taken to avoid damage to the engine.

NOTE:

A NOTE provides key information to make procedures easier or clearer.

NOTE:

- Yamaha continually seeks advancements in product design and quality. Therefore, while this manual contains the most current product information available at the time of printing, there may be minor discrepancies between your engine and this manual. If there is any question concerning this manual, please consult your Yamaha dealer.
- This manual should be considered a permanent part of this engine and should remain with this engine when resold.

CONTENTS

LIMITED WARRANTY (EF- AND EDL-SERIES)	1	PERIODIC MAINTENANCE	23
LOCATION OF IMPORTANT LABELS	3	MAINTENANCE CHART	23
SAFETY INFORMATION	5	SPARK PLUG INSPECTION	25
EXHAUST FUMES ARE		CARBURETOR ADJUSTMENT	25
POISONOUS	5	ENGINE OIL REPLACEMENT	26
FUEL IS HIGHLY FLAMMABLE AND		MUFFLER SCREEN AND SPARK	
POISONOUS	5	ARRESTER	27
ENGINE AND MUFFLER MAY		AIR FILTER	28
BE HOT	5	FUEL TANK FILTER	29
ELECTRIC SHOCK PREVENTION	6	BATTERY	30
CONNECTION NOTES	7	FUSE REPLACEMENT	31
CONNECTION	7	TROUBLESHOOTING	32
EXTENSION CORD NOTES	7	STORAGE	34
CONTROL FUNCTION	8	DRAIN THE FUEL	34
DESCRIPTION	8	ENGINE	34
CONTROL PANEL	8	BATTERY	35
OIL WARNING SYSTEM	9	RECOMMENDED BATTERY	35
ENGINE SWITCH	9	EXHAUST EMISSION CONTROL	
ECONOMY CONTROL SWITCH	10	SYSTEM AND COMPONENTS	36
DC PROTECTOR	10	SPECIFICATIONS	37
FUEL COCK KNOB	10	DIMENSIONS	37
PRE-OPERATION CHECK	11	ENGINE	37
FUEL	11	GENERATOR	37
ENGINE OIL	12	WIRING DIAGRAM	38
GROUND (Earth)	12		
BATTERY	13		
OPERATION	15		
STARTING THE ENGINE	15		
APPLICATION RANGE	17		
CONNECTION	18		
STOPPING THE ENGINE	22		

YAMAHA MOTOR CORPORATION U.S.A. EF- AND EDL-SERIES GENERATOR LIMITED WARRANTY

Yamaha Motor Corporation, U.S.A. hereby warrants that new Yamaha consumer generators purchased from an authorized Yamaha consumer generator dealer in the continental United States will be free from defects in material and workmanship for the period of time stated herein, subject to certain stated limitations.

THE PERIOD OF WARRANTY Any new EF-series or EDL-series Yamaha Generator purchased for private, non-commercial use from an authorized Yamaha consumer generator dealer in the continental United States will

be warranted against defects in material or workmanship for a period two (2) years from date of purchase, subject to exclusions noted herein. Any Yamaha non-commercial

generator purchased and utilized for commercial or rental applications will be warranted for a period one hundred eighty (180) days from the date of purchase, subject to exclusions noted herein.

DURING THE PERIOD OF WARRANTY any authorized Yamaha consumer generator dealer will, free of charge, repair or replace, at Yamaha's option, any part adjudged defective by Yamaha due to faulty workmanship or material from the factory. Parts used in warranty repairs will be warranted for the balance of the product's warranty period. All parts replaced under warranty become property of Yamaha Motor Corporation U.S.A.

GENERAL EXCLUSIONS from this warranty shall include any failures caused by:

- a. Installation of parts or accessories that are not qualitatively equivalent to genuine Yamaha parts.
- b. Abnormal strain, neglect, or abuse.
- c. Lack of proper maintenance.
- d. Accident or collision damage.

SPECIFIC EXCLUSIONS from this warranty shall include parts replaced due to normal wear or routine maintenance.

THE CUSTOMER'S RESPONSIBILITY under this warranty shall be to:

1. Operate and maintain the generator as specified in the appropriate Owner's Manual;

2. Give notice to an authorized Yamaha consumer generator dealer of any and all apparent defects within ten (10) days after discovery, and make the unit available at that time for inspection and repairs at such dealer's place of business.

WARRANTY TRANSFER: To transfer the warranty from the original purchaser to any subsequent purchaser(s), it is imperative that the unit be inspected and registered for warranty by an authorized Yamaha consumer generator dealer. In order for this warranty to remain in effect, this inspection and registration must take place within ten (10) days after transfer. An inspection and registration fee will be charged for this service. In no case will the warranty be extended beyond the original period.

YAMAHA MOTOR CORPORATION, U.S.A. MAKES NO OTHER WARRANTY OF ANY KIND, EXPRESSED OR IMPLIED. ALL IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE WHICH EXCEED THE OBLIGATIONS AND TIME LIMITS STATED IN THIS WARRANTY ARE HEREBY DISCLAIMED BY YAMAHA MOTOR CORPORATION, U.S.A. AND EXCLUDED FROM THIS WARRANTY.

SOME STATES DO NOT ALLOW LIMITATIONS ON HOW LONG AN IMPLIED WARRANTY LASTS, SO THE ABOVE LIMITATION MAY NOT APPLY TO YOU. ALSO EXCLUDED FROM THIS WARRANTY ARE ANY INCIDENTAL OR CONSEQUENTIAL DAMAGES INCLUDING LOSS OF USE. SOME STATES DO NOT ALLOW THE EXCLUSION OR LIMITATION OF INCIDENTAL OR CONSEQUENTIAL DAMAGES, SO THE ABOVE EXCLUSION MAY NOT APPLY TO YOU.

THIS WARRANTY GIVES YOU SPECIFIC LEGAL RIGHTS, AND YOU MAY ALSO HAVE OTHER RIGHTS WHICH VARY FROM STATE TO STATE.

YAMAHA MOTOR CORPORATION, U.S.A.
Post Office Box 6555
Cypress, California 90630

WARRANTY QUESTIONS AND ANSWERS

Q. What costs are my responsibility during the warranty period?

A. The customer's responsibility includes all costs of normal maintenance service, non-warranty repairs, accident damages, as well as oil and spark plugs.

Q. What are some examples of "abnormal" strain, neglect, or abuse?

A. These terms are general and overlap each other in areas. Specific examples include: Running the machine out of oil; lack of proper maintenance; operating the machine with a broken or damaged part which causes another part to fail; and so on. If you have any specific questions on operation or maintenance, please contact your dealer for advice.

Q. Does the warranty cover incidental costs such as transportation due to a failure?

A. No. The warranty is limited to repair of the machine itself.

Q. May I perform any or all of the recommended maintenance shown in the Owner's Manual instead of having the dealer do them?

A. Yes, if you are a qualified mechanic and follow the procedures specified in the Owner's and Service Manual. We do recommend, however, that items requiring special tools or equipment be done by a Yamaha generator dealer.

Q. Will the warranty be void or cancelled if I do not operate or maintain my new Yamaha exactly as specified in the Owner's Manual?

A. No. The warranty on a new Yamaha cannot be "voided" or "cancelled."

However, if a particular failure is caused by operation or maintenance other than as shown in the Owner's Manual, that failure may not be covered under warranty.

Q. What responsibility does my dealer have under this warranty?

A. Each Yamaha generator dealer is expected to:

1. Check the operation of the generator before sale.
2. Explain the operation, maintenance, and warranty requirements to your satisfaction at the time of sale, and upon your request at any later date.

In addition, each Yamaha generator dealer is held responsible for his setup, service and warranty repair work.

Q. Is the warranty transferable to second owners?

A. Yes. The remainder of the existing warranty can be transferred upon request.

The unit has to be inspected and reregistered by an authorized Yamaha generator dealer for the policy to remain effective.

CUSTOMER SERVICE

If your machine requires warranty service, you must take it to any authorized Yamaha generator dealer within the continental United States. Be sure to bring your warranty registration identification or other valid proof of the original date of purchase. If a question or problem arises regarding warranty, first contact the owner of the dealership. Since all warranty matters are handled at the dealer level, this person is in the best position to help you. If you are still not satisfied and require additional assistance, please write:

YAMAHA MOTOR CORPORATION U.S.A.
CUSTOMER RELATIONS DEPARTMENT
P.O. BOX 6555
Cypress, California 90630

CHANGE OF ADDRESS

The federal government requires each manufacturer to maintain a complete, up-to-date list of all first purchasers against the possibility of a safety-related defect and recall. This list is compiled from the purchase registrations sent to Yamaha Motor Corporation, U.S.A. by the selling dealer at the time of your purchase. If you should move after you have purchased your new generator, please advise us of your new address by sending a postcard listing your Yamaha model name, engine number, dealer number (or dealer's name) as it is shown on your warranty identification, your name and new mailing address. Mail to:


YAMAHA MOTOR CORPORATION, U.S.A.
WARRANTY DEPARTMENT
P.O. Box 6555
Cypress, California 90630

This will ensure that Yamaha Motor Corporation, U.S.A. has an up-to-date registration record in accordance with federal law.


LOCATION OF IMPORTANT LABELS

Please read the following labels carefully before operating this machine.

NOTE: _____
 Maintain or replace safety and instruction labels, as necessary.



792-052b




792-053b

①

HOT EXHAUST

***-28176-**

②

OIL**YAMAHA**

AC output **Hz
 Rated ***KVA
 ***V
 Phase Single
 DC output **V **A
 Fuel Gasoline

YAMAHA MOTOR CO., LTD.
 MADE IN JAPAN

③

IMPORTANT ENGINE INFORMATION

E M ENGINE FAMILY : ***** **YAMAHA**
 REFER TO OWNER'S MANUAL FOR MAINTENANCE SPECIFICATIONS AND ADJUSTMENTS.

DISPLACEMENT: *** ccf VALVE LASH (mm) IN: ***** EX: *****

IGNITION TIMING & IDLE MIXTURE NO OTHER ADJUSTMENTS NEEDED.

IDLE SPEED: ****~**** rpm AT NO LOAD


FUEL: THIS ENGINE IS CERTIFIED TO OPERATE ON UNLEADED GASOLINE.

ENGINE OIL: SAE 10W-30 TYPE SE

THIS ENGINE MEETS ****~**** CALIFORNIA EMISSION REGULATIONS FOR SMALL OFF-ROAD ENGINES.

THIS ENGINE CONFORMS TO PHASE 2 U.S.EPA REGULATIONS FOR SMALL NONROAD ENGINES.

EMISSIONS COMPLIANCE PERIOD: CATEGORY A (EPA)

ENGINE AIR INDEX (California only)

NOTE: THE LOWER THE AIR INDEX, THE LESS THE POLLUTION

THIS ENGINE IS CERTIFIED TO BE EMISSION COMPLIANT
 FOR THE FOLLOWING USE:

☐ MODERATE ☐ INTERMEDIATE ☒ EXTENDED

CHECK OWNERS MANUAL FOR FURTHER DETAILS

THIS LABEL TO BE REMOVED BY THE ULTIMATE PURCHASER ONLY!

YAMAHA MOTOR CO. LTD ***-2179R-00

④


⚠ WARNING

- READ THE OWNER'S MANUAL AND ALL LABELS BEFORE OPERATING.
- ONLY OPERATE IN WELL-VENTILATED AREA.
- EXHAUST GAS CONTAINS POISONOUS CARBON MONOXIDE.
- CHECK FOR SPILLED FUEL OR FUEL LEAKS.
- STOP ENGINE BEFORE REFUELING.
- DO NOT OPERATE NEAR FLAMMABLE MATERIALS.
- ELECTROCUTION CAN OCCUR IF GENERATOR IS USED IN RAIN, SNOW, OR NEAR WATER. KEEP THIS UNIT DRY AT ALL TIMES.

⚠ AVERTISSEMENT

- LISEZ LE MODE D'EMPLOI ET TOUTES LES ÉTIQUETTES AVANT DE FAIRE FONCTIONNER LA MACHINE.
- FAITES FONCTIONNER UNIQUEMENT DANS DES LIEUX BIEN AERES. LES GAZ D'ÉCHAPPEMENT CONTIENNENT DU MONOXYDE DE CARBONE.
- VÉRIFIEZ SI DU CARBURANT A ÉTÉ RENVERSE DU S'IL FUT.
- ARRÊTEZ LE MOTEUR AVANT DE FAIRE LE PLEIN DE CARBURANT.
- N'UTILISEZ PAS À PROXIMITÉ DE MATÉRIEAUX INFLAMMABLES.
- IL Y A RISQUE D'ELECTROCUTION SI LE GENERATEUR FONCTIONNE SOUS LA PLUIE, DANS LA NEIGE, OU PRES DE L'EAU. GARDEZ LA MACHINE AU SEC EN TOUTES CIRCONSTANCES.

7NJ-24162-10



AE00071

SAFETY INFORMATION

AE00072

EXHAUST FUMES ARE POISONOUS


- Never operate the engine in a closed area or it may cause unconsciousness and death within a short time. Operate the engine in a well ventilated area.



AE00075

FUEL IS HIGHLY FLAMMABLE AND POISONOUS

- Always turn off the engine when refuelling.
- Never refuel while smoking or in the vicinity of an open flame.
- Take care not to spill any fuel on the engine or muffler when refuelling.
- If you swallow any fuel, inhale fuel vapor, or allow any to get in your eye(s), see your doctor immediately. If any fuel spills on your skin or clothing, immediately wash with soap and water and change your clothes.
- When operating or transporting the machine, be sure it is kept upright. If it tilts, fuel may leak from the carburetor or fuel tank.




AE00843

ENGINE AND MUFFLER MAY BE HOT


- Place the machine in a place where pedestrians or children are not likely to touch the machine.






- Keep the machine at least 1 m (3 ft) from buildings or other equipment, or the engine may overheat.

① 1 m (3 ft)




- Avoid operating the engine with a dust cover.



- Be sure to carry the generator only by its carrying handle(s).


① Carrying handle(s) (shaded)




AE00083

ELECTRIC SHOCK PREVENTION

- Never operate the engine in rain or snow.



- Never touch the machine with wet hands or electrical shock will occur.



- Be sure to ground (earth) the generator.

NOTE: _____
Use ground (earth) lead of sufficient current capacity.

① Lead diameter

Ground (earth) Lead

Diameter:

0.12 mm (0.005 in)/ampere

EX;

10 Ampere → 1.2 mm (0.05 in)

AE00088

CONNECTION NOTES

- Avoid connecting the generator to commercial power outlet.
- Avoid connecting the generator in parallel with any other generator.

① Correct

② Incorrect

AE00091

CONNECTION


⚠ WARNING

Before the generator can be connected to a building's electrical system, a licensed electrician must install an isolation (transfer) switch in the building's main fuse box. The switch is the connection point for generator power and allows selection of generator or main line power to the building. This will prevent the generator from charging the main power line (backfeeding) when the main power supply has failed or has been turned off for line repair. Backfeeding can electrocute or injure line maintenance personnel. Also, generator and building electrical system damage can occur when normal operating power returns if unit is used without an isolation switch.


AE00086

EXTENSION CORD NOTES

- When using an extension cord, its total length should not exceed
 - { 60 meters for cross section of 1.5 mm square
 - and
 - { 100 meters for cross section of 2.5 mm square.
- This extension cord should be protected by a tough flexible rubber sheath (IEC 245) or the equivalent to withstand mechanical stresses.




CONTROL FUNCTION



AE00102

DESCRIPTION


- ① Recoil starter
- ② Oil filler cap
- ③ Oil drain plug
- ④ Battery box/Battery
- ⑤ Carrying handles (shaded)
- ⑥ Muffler
- ⑦ Fuel tank cap




AE00103

CONTROL PANEL

- ① Engine switch
- ② Economy control switch
- ③ DC receptacle
- ④ AC receptacle
- ⑤ Ground (Earth) terminal
- ⑥ Overload indicator light
- ⑦ AC pilot light
- ⑧ DC protector
- ⑨ Oil warning light
- ⑩ Choke knob
- ⑪ Fuel cock knob






AE00111

OIL WARNING SYSTEM

When the oil level falls below the lower level, the engine stops automatically. Unless you refill with oil, the engine will not start again.

NOTE:

If the engine stalls or does not start, turn the engine switch to "ON" position and then pull the recoil starter. If the oil warning light flickers for a few seconds, the engine oil is insufficient. Add oil and restart.



AE00896

ENGINE SWITCH

The engine switch controls the ignition system.

①  "ON"


Ignition circuit is switched on.

The engine runs on its position.

②  "STOP"

Ignition circuit is switched off.

The engine will not run.


③  "START"

Starting circuit is switched on.

The starter motor starts and the engine can be started.

CAUTION:

Take your hand off the switch immediately after the engine starts.



AE00988

ECONOMY CONTROL SWITCH

① I “ON”


When the economy control switch is turned “ON”, the economy control unit controls the engine speed according to the connected load. The results are better fuel consumption and less noise.

② ○ “OFF”

When the economy control switch is turned “OFF”, the engine runs at the rated r/min (3,800 r/min) regardless of whether there is a load connected or not.

NOTE:

The economy control switch must be turned to “○” (OFF) when using electric devices that require a large starting current, such as a compressor or a submersible pump.



AE00911

DC PROTECTOR



The DC protector turns off automatically when the load exceeds the generator rated output.

CAUTION:

Reduce the load to the specified generator rated output if the DC protector turns off. If it turns off again, consult a Yamaha dealer.

NOTE:

Press to reset the DC protector.



AE01048


FUEL COCK KNOB

The fuel cock knob is used to supply fuel from the fuel tank to the carburetor.

PRE-OPERATION CHECK

NOTE: _____


Pre-operation checks should be made each time the generator is used.



⚠ WARNING _____

The engine and muffler will be very hot after the engine has been run.

Avoid touching the engine and muffler while they are still hot with any part of your body or clothing during inspection or repair.



AE00856

FUEL


Make sure there is sufficient fuel in the tank.

Recommended fuel:

Unleaded gasoline


Fuel tank capacity:

Total: 13.0 L (2.86 Imp gal, 3.43 US gal)



Your Yamaha engine has been designed to use regular unleaded gasoline with a pump octane number $((R + M)/2)$ of 86 or higher, or research octane number of 91 or higher.


① Fuel level gauge




"F"	Full
"E"	Empty

⚠ WARNING _____

- Fuel is highly flammable and poisonous. Check "SAFETY INFORMATION" (See page 5) carefully before refueling.
- Do not fill above the top of the fuel filter or it may overflow when the fuel heats up later and expands.
- Wipe up any spilled fuel immediately.
- After refueling, make sure the tank cap is tightened securely.






AE00222

ENGINE OIL

Make sure the engine oil is at the upper level of the oil filler hole.

Add oil as necessary.




① Upper level

Recommended oil:

- ☐ A YAMALUBE 4 (10W-30) or SAE 10W-30 type SE motor oil
- ☐ B SAE #30
- ☐ C SAE #20
- ☐ D SAE 10W

Engine oil quantity:


0.6 L (0.53 Imp qt, 0.63 US qt)



NOTE:


Recommended engine oil classification:

API Service "SE" or "SF".



CAUTION:

The generator has been shipped without engine oil. Fill with oil or it will not start.



AE00241

GROUND (Earth)






Make sure to ground (earth) the generator.

Check "SAFETY INFORMATION" on page 6.

AE01083

BATTERY (See page 30)


Installation




1. Loosen the bolts ① and remove the cover ②.
2. Loosen the bolts ③ and remove the battery box ④.
3. Remove the band ⑤ to remove the battery ⑥.
4. Fill the battery with the electrolyte.
Refer to the instruction sheet included with the electrolyte for filling instructions.
5. Turn the engine switch to the “STOP” position to prevent accidental short circuiting.
6. Install the battery onto the battery box.
7. Connect the positive lead ① to the positive battery terminal ②, then the negative lead ③ to the negative battery terminal ④.

NOTE:


- Clamp the red wire to the positive (+) terminal first, then the black wire to the negative (-) terminal of the battery. Do not reverse these positions.
- For EF3000iSEB, tighten the two positive battery leads (one from the starter relay and one from the DC-DC converter) to the same positive terminal and the two negative battery leads (one from the engine and one from the DC-DC converter) to the same negative terminal.



8. Secure it with the band.
9. Install the battery box ⑤ and tighten the bolts ⑥.



10. Install the cover ⑦ and tighten the bolts ⑧.



⚠ WARNING

Battery electrolyte is poisonous and dangerous, causing severe burns, etc. It contains sulfuric (sulphuric) acid. Avoid contact with skin, EYES or clothing.

Antidote:

EXTERNAL-Flush with water.

INTERNAL-Drink large quantities of water or milk. Follow with milk of magnesia, beaten egg or vegetable oil. Call physician immediately.

Eyes: Flush with water for 15 minutes and get prompt medical attention. Batteries produce explosive gases. Keep sparks, flame, cigarettes, etc. away. Ventilate when charging or using in closed space. Always cover eyes when working near batteries. **KEEP OUT OF REACH OF CHILDREN.**

OPERATION

NOTE:

The generator has been shipped without engine oil. Fill with oil or it will not start.

① Upper level

STARTING THE ENGINE

NOTE:

- Before starting the engine, do not connect any electric devices.
- Turn the economy control switch to the “○” (OFF) position.

① ○ “OFF”

1. Turn the fuel cock knob to the “ON” position.

① “ON”

2. Pull the choke knob fully out.

① Choke knob







NOTE:

The choke is not required to start a warm engine. Push the choke knob in to the original position.

Electric Starting:


3. Turn the engine switch to the “Ⓔ” (START) position.

① Ⓔ “START”



CAUTION:


- Take your hand off the switch immediately after the engine starts.
- If the engine fails to start, release the switch, wait a few seconds, then try again. Each attempt should be as short as possible to preserve the battery. Do not crank the engine more than 10 seconds on any one attempt.



4. After the engine starts, warm up the engine until the engine does not stop when the choke knob is returned to the original position.
5. Push the choke knob back to the original position.

NOTE:


When starting the engine in areas where the ambient temperature is below 0°C (32°F), the engine automatically operates at the rated r/min (3,800 r/min) for three minutes to warm up the engine regardless of the economy control switch position. The economy control unit operates normally afterwards if the economy control switch is turned to "I" (ON).



Manual Starting:





3. Turn the engine switch to the "ON" (ON) position.

① ⚡ "ON"



4. Pull slowly on the recoil starter until it is engaged, then pull it briskly.
5. After the engine starts, warm up the engine until the engine does not stop when the choke knob is returned to the original position.
6. Push the choke knob back to the original position.


APPLICATION RANGE

AC				DC 
Power factor	1	0.8–0.95	0.4–0.75 (Efficiency 0.85)	
EF3000iSE EF3000iSEB	–2,800W	–2,240W	–950W	Rated voltage 12V Rated current 12A

NOTE:

- “–” means below.
- Application wattage indicates when each device is used by itself.
- The simultaneous usage of AC and DC power is possible but total wattage should not exceed the rated output.

EX:



Generator rated output		2,800VA
Frequency	Power factor	
AC	1.0	–2,650W
	0.8	–2,100W
DC	—	144W (12V/12A)

- The overload indicator light ① comes on when total wattage exceeds the application range. (See page 19 for more details.)

CAUTION:

Be sure the total load is within generator rated output otherwise generator damage will occur.

NOTE:





Some precision equipment is voltage sensitive and may require a more uniform voltage supply than portable generators provide. Examples include some medical equipment, personal computers, and some inverters that sense peak and RMS voltage values. Consult the precision-equipment vendor before relying on any portable generator to provide power to such equipment.

CONNECTION

Alternating Current (AC)

CAUTION:

- Be sure all electric devices including the lines and plug connections are in good condition before connection to the generator.
- Be sure any electric devices are turned off before plugging it in.
- Be sure the total load is within generator rated output.
- Be sure the receptacle load current is within receptacle rated current.



1. Wind the power lead 2 or 3 turns around handle.
2. Start the engine.
3. Plug in to the AC receptacle.

4. Make sure the AC pilot light is on.


① AC pilot light

5. Turn the economy control switch to the "I" (ON) position and turn on any electric devices.

① I (ON)

NOTE:

The economy control switch must be turned to "O" (OFF) when using electric devices that require a large starting current, such as a compressor or a submergible pump.



AE01087

Overload indicator light

The overload indicator light ① comes on when an overload of a connected electrical device is detected, the inverter control unit overheats, or the AC output voltage rises. The electronic breaker will then activate, stopping power generation in order to protect the generator and any connected electric devices. The AC pilot light (green) will go off and the overload indicator light (red) will stay on, but the engine will not stop running.

When the overload indicator light comes on and power generation stops, proceed as follows:

1. Turn off any connected electric devices and stop the engine.
2. Reduce the total wattage of connected electric devices within the application range.
3. Check for blockages in the cooling air inlet and around the control unit. If any blockages are found, remove.
4. After checking, restart the engine.

NOTE:





- The generator AC output automatically resets when the engine is stopped and then restarted.
- The overload indicator light may come on for a few seconds at first when using electric devices that require a large starting current, such as a compressor or a submersible pump. However, this is not a malfunction.
- For EF3000iSEB, the overload indicator light may flash when using electric devices that require a large starting current. However, this is not a malfunction. (The flashing indicator is a result of the generator temporarily discharging more than its rated wattage.)

While the overload indicator light is flashing, electric devices that require a large starting current cannot be started.

Battery Charging

NOTE:

The generator DC rated voltage is 12V.



1. Wind the battery charging lead (furnished as an accessory) 2 or 3 turns around the handle and plug into DC receptacle.

NOTE:

- Make connections to the battery after starting the engine.
- Clamp the red wire to the positive (+) terminal and the black wire to the negative (-) terminal of the battery. Do not reverse these positions.

- ① Red
- ② Black

2. Start the engine.
3. Press in the DC protector and install the battery.

CAUTION:

- Be sure the battery leads are properly connected.
- Be sure the breather hose is properly connected and is not damaged or obstructed.
- Reduce the load to the specified generator rated output if the DC protector turns off. If it turns off again, consult a Yamaha dealer.


NOTE:

Press to reset the DC protector.

- ① "ON"
- ② "OFF"

NOTE:

- At full charge, electrode specific gravity is between 1.26 and 1.28.
- Check specific gravity hourly.



⚠ WARNING

Never smoke or make and break connections at the battery while charging. Sparks may ignite the battery gas.

Battery electrolyte is poisonous and dangerous, causing severe burns, etc. contains sulfuric (sulphuric) acid. Avoid contact with skin, eyes or clothing.

Antidote:



EXTERNAL-Flush with water.

INTERNAL-Drink large quantities of water or milk. Follow with milk of magnesia, beaten egg or vegetable oil. Call physician immediately.

EYES: Flush with water for 15 minutes and get prompt medical attention. Batteries produce explosive gases. Keep sparks, flame, cigarettes, etc., away. Ventilate when charging or using in closed space. Always cover eyes when working near batteries. **KEEP OUT OF REACH OF CHILDREN.**




STOPPING THE ENGINE**NOTE:** _____

- Turn off any electric devices.
- Turn the economy control switch to the “○” (OFF) position.



① ○ “OFF”

1. Disconnect any electric devices.

2. Turn the engine switch to the “” (STOP) position.①  “STOP”

3. Turn the fuel cock knob to “OFF”.

① “OFF”

PERIODIC MAINTENANCE

AE00403

MAINTENANCE CHART

Regular maintenance is most important for best performance and safe operation.

WARNING

Stop the engine before starting maintenance work.

No.	Item	Remarks	Pre-Operation check (daily)	Initial	Every			
				1 month or 20 Hr	3 months or 50 Hr	6 months or 100 Hr	12 months or 300 Hr	
1.	** Spark Plug	Check condition. Adjust gap and clean. Replace if necessary.			●			
2.*	** Valve Clearance	Check and adjust when engine is cold.					●	
3.*	** Crankcase breather system	Check breather hose for cracks or damage. Replace if necessary.					●	
4.*	** Idle speed	Check and adjust engine idle speed.					●	
5.	** Exhaust System	Check for leakage. Retighten or *replace gasket if necessary.	●					
		Check muffler screen and spark arrestor. Clean/ replace if necessary.					●	
6.	Engine Oil	Check oil level	●					
		Replace		●		●		
7.	** Air Filter	Clean. Replace if necessary.			●			

* : It is recommended that these items be serviced by a Yamaha dealer.

** : Related to emission control system.




No.	Item	Remarks	Pre-Operation check (daily)	Initial	Every		
				1 month or 20 Hr	3 months or 50 Hr	6 months or 100 Hr	12 months or 300 Hr
8.	Fuel Filter	Clean fuel tank filter. Replace if necessary.				●	
9.	Fuel Line	Check fuel hose for crack or damage. *Replace if necessary.	●				
10.	** Choke knob	Check choke operation.	●				
11.	Cooling System	Check for fan damage.					●
12.	Starting System	Check recoil starter operation.	●				
		Check electric starter operation	●				
13.*	** Decarbonization	More frequently if necessary.					●
14.	Generation	Check the pilot light comes on.	●				
15.*	Fittings/ Fasteners	Check all fittings and fasteners. Correct if necessary.				●	

* : It is recommended that these items be serviced by a Yamaha dealer.

** : Related to emission control system.

CAUTION:

Use only Yamaha specified genuine parts for replacement. Ask an authorized Yamaha dealer for further attention.



AE01051

SPARK PLUG INSPECTION

You should periodically remove and inspect the spark plug.

1. Loosen the bolt ① and remove the side cover ②.
2. Remove the spark plug cap and the spark plug.
3. Check for discoloration and remove the carbon.

Standard electrode color:
Tan Color

4. Check the spark plug type and gap.

Standard Spark Plug:
BPR4ES (NGK)
Spark Plug Gap:
0.7–0.8 mm (0.028–0.031 in)

Ⓐ Gap

5. Install the spark plug.





Spark Plug Torque:
17.5 N•m (1.75 kgf•m, 13 lbf•ft)

6. Install the spark plug cap.
7. Install the side cover and tighten the bolt.

AE00431

CARBURETOR ADJUSTMENT

The carburetor is a vital part of the engine. Adjusting should be left to a Yamaha dealer with the professional knowledge, specialized data, and equipment to do so properly.



ENGINE OIL REPLACEMENT

1. Place the machine on a level surface and warm up the engine for several minutes.
Then stop the engine.
2. Loosen the bolt (1) and remove the cover (2).
3. Remove the rubber cap (3) and the oil filler cap (4).
4. Place an oil pan under the engine. Remove the oil drain plug (5) so that the oil can be completely drained.
5. Check the drain plug, gasket (6), oil filler cap and O-ring (7).
If damaged, replace.
6. Reinstall the oil drain plug.

Drain Plug Torque:
17 N•m (1.7 kgf•m, 12 lbf•ft)

7. Add engine oil to the upper level.

① Upper level

Recommended oil:

- [A] YAMALUBE 4 (10W-30) or SAE 10W-30 type SE motor oil
- [B] SAE #30
- [C] SAE #20
- [D] SAE 10W

Engine oil quantity:
0.6 L (0.53 Imp qt, 0.63 US qt)


NOTE: _____

Recommended engine oil classification:
API Service "SE" or "SF".

CAUTION: _____


Be sure no foreign material enters the crankcase.

8. Install the oil filler cap, the rubber cap and the cover.


MUFFLER SCREEN AND SPARK ARRESTER**⚠ WARNING**

The engine and muffler will be very hot after the engine has been run.

Avoid touching the engine and muffler while they are still hot with any part of your body or clothing during inspection or repair.




1. Remove the cover and heat-protection cover.




2. Remove the muffler cap and the muffler screen.

- ① Screw
- ② Muffler cap
- ③ Muffler screen




3. Use a flathead screw driver to pry the spark arrester out from the muffler.



4. Remove the spark arrester.

- ① Spark arrester




5. Remove the carbon deposits on the muffler screen and spark arrester using a wire brush.

CAUTION:

When cleaning, use the wire brush lightly to avoid damaging or scratching of the muffler screen and spark arrester.

6. Check the muffler screen and spark arrester.
Replace them if damaged.




7. Install the spark arrester.


NOTE: _____

Align the spark arrester projection with the hole in the muffler pipe.

- ① Projection
- ② Hole




8. Install the muffler screen and the muffler cap.




AE01084

AIR FILTER

1. Loosen the bolt ① and remove the cover ②.




2. Remove the clip ③ holding the air filter cover ④.
3. Remove the air filter cover and element.



4. Wash the foam element in solvent and dry.
5. Oil the foam element and squeeze out excess oil.
The foam element should be wet but not dripping.

Recommended oil:
Foam-air-filter oil
or
SAE #20 motor oil



CAUTION:

Do not wring out the element.
This could cause it to tear.

6. Insert the element into the air filter.

NOTE:

Be sure the element sealing surface matches the air filter so there is no air leak.

CAUTION:

The engine should never run without the element; excessive piston and cylinder wear may result.

WARNING

Never use solvent while smoking or in the vicinity of an open flame.

7. Replace the air filter cover in its original position and install the clip.
8. Install the cover and tighten the bolt.

AE00471

FUEL TANK FILTER


1. Remove the fuel tank cap and filter.

① Filter

2. Clean the filter with solvent. If damaged, replace.
3. Wipe the filter and insert it.

WARNING

Be sure the tank cap is tightened securely.



BATTERY


This generator is equipped with a sealed-type (MF) battery, which does not require any maintenance. There is no need to check the electrolyte or to add distilled water.

To charge the battery

Have a Yamaha dealer charge the battery as soon as possible if it seems to have discharged.

CAUTION:

To charge a sealed-type (MF) battery, a special (constant-voltage) battery charger is required. Using a conventional battery charger will damage the battery. If you do not have access to a sealed-type (MF) battery charger, have a Yamaha dealer charge your battery.

**⚠ WARNING**

Battery electrolyte is poisonous and dangerous, causing severe burns, etc. It contains sulfuric (sulfuric) acid. Avoid contact with skin, EYES or clothing.

Antidote:

EXTERNAL-Flush with water.

INTERNAL-Drink large quantities of water or milk. Follow with milk of magnesia, beaten egg or vegetable oil. Call physician immediately.

Eyes: Flush with water for 15 minutes and get prompt medical attention. Batteries produce explosive gases. Keep sparks, flame, cigarettes, etc. away. Ventilate when charging or using in closed space. Always cover eyes when working near batteries. **KEEP OUT OF REACH OF CHILDREN.**

FUSE REPLACEMENT**⚠ WARNING**

Be sure to use specified fuse. A wrong fuse will cause electrical system damage and A FIRE HAZARD.

CAUTION:



Be sure the engine switch is turned to “STOP” to prevent accidental short circuiting.






1. Remove the side cover ① and the battery box ②. (See page 30; “BATTERY”.)
2. Replace the blown fuse with one of proper amperage.

Specified fuse: 10 A

NOTE:

If the fuse immediately blows again, consult a Yamaha dealer.





AE01078

TROUBLESHOOTING

Engine won't start

1. Fuel systems

- No fuel supplied to combustion chamber.
 - No fuel in tank Supply fuel.
 - Fuel in tank Fuel cock knob to "ON".
 - Clogged fuel line Clean fuel line.
 - Clogged carburetor Clean carburetor.

2. Engine oil system

- Insufficient
 - Oil level is low Add engine oil.

3. Electrical systems

- Engine switch to "ON".
 - Poor spark
 - Spark plug dirty with carbon or wet Remove carbon or wipe spark plug dry.
 - Faulty ignition system Consult dealer.

4. Compression

- Insufficient
 - Worn out piston and cylinder Consult dealer.
 - Loose cylinder head nuts Tighten nuts properly.
 - Damaged gasket Replace gasket.

AE00785



Generator won't produce power

- Safety device (AC) to "OFF" Stop the engine, then restart.
- Safety device (DC protector) to "OFF" Press to reset the DC protector.

A ENGINE DOES NOT START



B Turn the engine switch to "ON", then pull the recoil starter and check if the oil warning light flickers.





C Does not flicker

D Flickers.



E Check engine oil level.



F OK


G Level low

Consult a Yamaha dealer.

Add engine oil.



H Pull the recoil starter and check the spark plug for spark strength. (See "WARNING")



⚠ WARNING

- To prevent FIRE HAZARDS be sure fuel is not present in the spark plug area.
- To prevent FIRE HAZARDS be sure to place the spark plug as far way as possible from the spark plug hole and carburetor area.
- To prevent ELECTRIC SHOCK do not hold spark plug lead with hand while testing.



I Engine does not start.

J Engine starts.



K Check the spark plug.

- Type:
- Gap:



L Incorrect

M OK

Replace or Adjust Gap.

Clean the spark plug.



N Check the following

- Fuel line clogging
- Air cleaner element clogging.

O Clogged

P OK



Q Clean or Replace; Consult a Yamaha dealer.

R Consult a Yamaha dealer.


STORAGE

Long term storage of your machine will require some preventive procedures to guard against deterioration.

AE01056

DRAIN THE FUEL

1. Remove the fuel tank cap. Drain the fuel from the fuel tank into an approved gasoline container using a commercially available hand siphon. Then, install the fuel tank cap.



⚠ WARNING



- **Fuel is highly flammable and poisonous. Check “SAFETY INFORMATION” (See page 5) carefully.**
- **Wipe up any spilled fuel immediately.**


2. Drain fuel from the carburetor by loosening the drain screw ① on the carburetor float chamber.
3. Turn the fuel cock knob to “OFF”. Start the engine and leave it run until it stops. This will burn any remaining fuel in the carburetor.

AE01079

ENGINE

1. Remove the spark plug, pour about one tablespoon of SAE 10W30 or 20W40 motor oil into the spark plug hole and reinstall the spark plug. Recoil start the engine by turning over several times (with ignition off) to coat the cylinder walls with oil.
2. Pull the recoil starter until you feel compression. Then stop pulling. (This prevents the cylinder and valves from rusting).
3. Clean exterior of the generator and apply a rust inhibitor.
4. Store the generator in a dry, well-ventilated place, with the cover placed over it.
5. The generator must remain in a vertical position when stored, carried or operated. The caster lock lever should be in the “LOCK” position when stored or operated.





AE01086

BATTERY

1. Remove the battery.
2. Store the battery in a cool, dark and dry place and charge it once a month.

Do not store the battery in an excessively warm or cold place [i.e., less than 0°C (30°F) or more than 30°C (90°F)].

⚠ WARNING

- Disconnect the negative lead first, then the positive lead from the battery.
- Connect the positive lead first, then the negative lead to the battery when installing the battery.
- Be sure the battery terminals are tight.

CAUTION:

- Do not disconnect the battery during engine operation.
- Avoid operating the generator with the battery removed.

AE01057

RECOMMENDED BATTERY

Recommended battery:
Capacity: 12V/10A•h

NOTE:

- Clamp the red wire to the positive (+) terminal and the black wire to the negative (-) terminal of the battery. Do not reverse these positions.
- Be sure the battery is installed on the battery box.

**EXHAUST EMISSION CONTROL SYSTEM
AND COMPONENTS**

Item	Acronym
• CARB. ASSY., LH. & JT., CARBURETOR2	CARB (Carburetor)
• T.C.I. MAGNETO ASSY. & PLUG, SPARK	EI (Electronic Ignition)
• CRANKCASE1 & HEAD, CYLINDER1 Ventilation)	PCV (Positive Crankcase
• AIR FILTER ASSY.	ACL (Air Cleaner)
• MUFF., 2, CAP, NET, WIRE2 & ARRESTER, SPARK	

The above items and the corresponding acronyms are provided in accordance with U.S. EPA REGULATIONS FOR NEW NONROAD SPARK-IGNITION NONHANDHELD ENGINES and the CALIFORNIA REGULATIONS FOR 1995 AND LATER SMALL OFF-ROAD ENGINES.

The acronyms conform to the latest version of the SAE's recommended practice document J1930, "Diagnostic Acronyms, Terms, and Definitions For Electrical/Electronic System".

It is recommended that these items be serviced by a Yamaha dealer.

SPECIFICATIONS

DIMENSIONS

	Unit	EF3000iSE	EF3000iSEB
Overall Length	mm (in)	680 (26.8)	
Overall Width	mm (in)	445 (17.5)	
Overall Height	mm (in)	555 (21.9)	
Dry Weight	kg (lb)	67 (147.7)	69 (152.1)

ENGINE

	Unit	EF3000iSE	EF3000iSEB
Type		Forced air cooled 4-stroke gasoline OHV	
Cylinder Arrangement		Inclined, 1 cylinder	
Displacement	cm ³	171	
Bore × Stroke	mm (in)	66.0 × 50.0 (2.60 × 1.97)	
Rated Output	kW(HP)/r/min	3.5 (4.7)/3,800	
Operation Hours at rated operation	Hr	8.0	
Fuel		Unleaded gasoline	
Fuel Tank Capacity	L (Imp gal, US gal)	13.0 (2.86, 3.43)	
Engine Oil Quantity	L (Imp qt, US qt)	0.6 (0.53, 0.63)	
Ignition System		TCI	
Spark Plug: Type Gap	mm (in)	BPR4ES (NGK) 0.7–0.8 (0.028–0.031)	
Noise Level*	dB (A)	57	

*: Measured at rated operation from 7 m (23 ft) distance.

GENERATOR


	Unit	EF3000iSE	EF3000iSEB
AC Output			
Rated Voltage	V	120	
Rated frequency	Hz	60	
Rated current	A	23.3	
Rated Output	kVA	2.8	
Safety Device: Type		Electronic	
DC Output			
Rated voltage	V	12	
Rated current	A	12	
Safety Device: Type		DC protector	



- ### Color code

B	Black
Br	Brown
G	Green
Gy	Gray
L	Blue
O	Orange
R	Red
W	White
Y	Yellow
B/W	Black/White
R/W	Red/White
G/Y	Green/Yellow
W/L	White/Blue

WIRING DIAGRAM **EF3000iSEB**



770-045

- | | | | | | | | | | | | | | | | | | | | | | | | |
|-------------|------------|----------------|----------------|------------------|-----------------|---------------------------|--------------------------|----------------------------|-----------------|--------------------------|-----------------|---------------------|--------------------------|-------------------|---------------|--------------|------------------|------------------|-------------------|-------------|-----------|-----------------|-----------------|
| ① Main coil | ②③ DC coil | ④ DC rectifier | ⑤ Control unit | ⑥ AC pilot light | ⑦ AC receptacle | ⑧ Ground (Earth) terminal | ⑨ Economy control switch | ⑩ Overload indicator light | ⑪ DC receptacle | ⑫ DC protector (breaker) | ⑬ Engine switch | ⑭ Oil warning light | ⑮ Speed limiter assenbly | ⑯ Oil level gauge | ⑰ T.C.I. unit | ⑱ Spark plug | ⑲ T.C.I. magneto | ⑳ Stepping motor | ㉑ DC-DC converter | ㉒ Rectifier | ㉓ Battery | ㉔ Starter relay | ㉕ Starter motor |
|-------------|------------|----------------|----------------|------------------|-----------------|---------------------------|--------------------------|----------------------------|-----------------|--------------------------|-----------------|---------------------|--------------------------|-------------------|---------------|--------------|------------------|------------------|-------------------|-------------|-----------|-----------------|-----------------|

Color code

B	Black
Br	Brown
G	Green
Gy	Gray
L	Blue
O	Orange
R	Red
W	White
Y	Yellow
B/W	Black/White
R/W	Red/White
G/Y	Green/Yellow
W/L	White/Blue

— MEMO —

— MEMO —

— MEMO —


— MEMO —


— MEMO —

— MEMO —

PRINTED ON RECYCLED PAPER



PRINTED IN JAPAN
02 • 10 – 0.4 × 1 



PLACE
STAMP
HERE

**YAMAHA MOTOR CORPORATION U.S.A.
P.O. BOX 6555
CYPRESS, CALIFORNIA 90630**

ATTN: WARRANTY DEPARTMENT

CUSTOMER WARRANTY REGISTRATION

OWNER'S
NAME _____

DATE SOLD

MODEL

MACHINE SERIAL NUMBER

ADDRESS _____

CITY &
STATE _____

ZIP _____

AREA CODE

PHONE NUMBER () _____

IMPORTANT!

- Please complete and mail this form. It will help ensure that Yamaha has accurately registered your purchase for warranty.
- Manufacturers are required to maintain a complete up-to-date list of all first purchasers of products against the possibility of a safety-related defect and recall.
- Please check the box that best describes the primary area of usage of this product:

☐ Private

☐ Commercial

☐ Rental

MAIL THIS TO YAMAHA MOTOR CORPORATION, U.S.A.