

# ASSEMBLY AND INSTALLATION INSTRUCTIONS

CH1011/CH11814

**WARNING:** TO AVOID RISK OF ELECTRICAL SHOCK, BE SURE TO SHUT OFF POWER WHILE INSTALLING OR SERVICING THIS FIXTURE.

NOTE: Before installing, consult local electrical codes for wiring and grounding requirements.

## Installation Steps

1. Secure the loop to the nipple-2.
  2. Adjust the arms of the fixture according to the drawing of the package.
- Important to know:**
- a. The distance between the arms should be equally distanced.
  - b. The arms should be fixed securely.
3. Secure the metal ring to the fixture arms with set screws.
  4. Thread the nipple-1 to the mounting strap, and secure with a washer and a lock nut.
  5. Attach the mounting strap to ceiling box by using 2 mounting screws.
  6. Choose a certain length of chain you need, then weave the fixture wire and the ground wire through the chain links. Spread one end link of chain to clamp securely to the loop.
  7. Secure the top loop to the nipple.
  8. Thread the fixture wire and grounding wire through collar, canopy, top loop, nipple and mounting strap in order.

9. Clamp the other end link of chain to the top loop.
10. Make wire connections with wire nuts:
  - Connect smooth wire (marked) from fixture to black wire from power source.
  - Connect ridged wire (marked) from fixture to white wire from power source.
  - Attach the grounding wire and house grounding wire to mounting strap with a green grounding screw. Carefully tuck wires back into the outlet box.
11. Attach the canopy to the mounting strap by inserting the top loop, and secure with the collar.
12. Thread the nipple-3 into the coupling, and secure with a washer and lock nut. (You can adjust the length of the nipple-3 with the lock nut.)
13. Attach the central glass to the fixture by inserting the nipple-3, and secure with a plastic pad, a metal pad and a lock nut.
14. Attach the cap onto the nipple-3, and secure with the finial.
15. Set the bobeches to the lamp holders, attach the side rings on the bobeches, and attach the candle covers to the side sockets.
16. Install bulbs. (Please do not exceed the maximum capacity which is recommended on the package.)
17. Turn on the power at fuse or circuit box.

