

**ASSEMBLY & INSTALLATION  
INSTRUCTIONS  
FOR  
4960, 4963, 4964 SERIES**

*Please read carefully and save these instructions, as you may need them at a later date.*

**CAUTION**

Turn off the main power at the circuit breaker before installing the fixture, in order to prevent possible shock.

**GENERAL**

All electrical connections must be in accordance with local and National Electrical Code (N.E.C.) standards. If you are unfamiliar with proper electrical wiring connections obtain the services of a qualified electrician.

Remove the fixture and the mounting package from the box and make sure that no parts are missing by referencing the illustrations on the installation instructions.

**ASSEMBLY AND INSTALLATION**

**NOTE:** The OFFSET SCREWDRIVER (19) specified in Steps 3 and 5 can be purchased at a local hardware store.

1. Thread the MOUNTING BRACKET (2) onto the NIPPLE (5) until it reaches the 1/8 IPS HEX NUT (4).
2. Slide the COVER CUP (14) toward the SOCKET CUP (15).
3. Using an OFFSET SCREWDRIVER (19) (not provided), attach the FIXTURE GROUND WIRE (7) and the POWER SUPPLY GROUND WIRE (6) to the MOUNTING BRACKET (2) by means of the GROUND SCREW (8).
4. Attach the power supply wires to the fixture lead wires by connecting the BLACK SUPPLY WIRE (10) to the BLACK FIXTURE WIRE (11), and the WHITE SUPPLY WIRE (12) to the WHITE FIXTURE WIRE (13) using WIRE NUTS (9). Tuck the wires into OUTLET BOX (1).
5. Using an OFFSET SCREWDRIVER (19) (not provided), attach the MOUNTING BRACKET (2) to the OUTLET BOX (1) using the #8-32 IPS MOUNTING SCREWS (3).

**ASSEMBLY AND INSTALLATION (Continued)**

6. Slide the COVER CUP (14) toward the OUTLET BOX (1) until it reaches the mounting wall. Then, thread the CUP HOLDING SCREW (18) into the hole provided on the COVER CUP (14) and tighten it with a screwdriver.
7. Slide the GLASS SHADE(S) (16) over the SOCKET(S) (20) and secure it (them) into place using the SOCKET RING(S) (17).
8. Screw light bulb(s) into the SOCKET(S) (20). Be sure that the lamp wattage specified on the fixture's wattage label is not exceeded.

**INSTALLATION IS NOW COMPLETED**

