



NATURE POWER 100 WATT POWER INVERTER



Features

Convert battery power to household AC power installation.

- 1 x AC Outlet Charging Computers, Runs Fan, Small Power Tools and More
- 2 Amp USB Outlet Charges Tablets, Phones and Most Portable Electronics
- 100 Watt Continuous Output, 200 Watts Surge
- Compact – Easily Stores in any Vehicle or Purse



SPECIFICATIONS

AC OUTPUT

Power: 100W (Continuous), 200W(Peak)

Voltage: 115±10 Vac

Frequency: 60±3

Waveform: Modified sinewave

AC Outlet: 1 x 3Prong AC outlet

DC OUTPUT

USB: 1 x 5V/2A

DC INPUT

Voltage (nominal): 12.8-13.2Vdc

Operation Range: 10.0-15.0Vdc

Material: ABS, Stell

PROTECTION:

Input Undervoltage Shutdown/Warning: 10.0±0.5Vdc

Input Undervoltage Recovery: 12.0±0.5Vdc

Input Overvoltage Shutdown: 15.5±0.5Vdc

Overload Shutdown: Yes

Output Short circuit Protection: Yes

Over Temperature Shutdown: Yes

SHIPPING DETAILS

Item Number: 37100

UPC Code: 839290003008

Country of Origin: China / Taiwan

Product Dimensions: 5.4 x 2.4 x 1 in

Color box Dimensions: 5.8 x 2.6 x 1.2 in

Product Weight: 0.33 lbs with package

0.24 lbs without package

Master Quantity: -

Master Dimensions: - in

Master Weight: - lbs



1-800-588-0590

www.naturepowerproducts.com



fb.me/NaturePowerProducts

