


# **MINI PENDANT FITTER**

MODEL #CPL2BNK

Français p. 9

Español p. 18





DAMP LOCATIONS

### ATTACH YOUR RECEIPT HERE

Serial Number \_\_\_\_\_ Purchase Date \_\_\_\_\_




**Questions, problems, missing parts?** Before returning to your retailer, call our customer service department at **1-800-643-0067**, 8 a.m. - 6 p.m., EST, Monday - Thursday, 8 a.m. - 5 p.m., EST, Friday.




# **PACKAGE CONTENTS**

PART	DESCRIPTION	QUANTITY
Α	Fixture	1
В	Mounting Strap (preassembled to fixture (A))	1
С	Socket Ring (preassembled to fixture (A))	1



# **HARDWARE CONTENTS** (shown actual size)





# **SAFETY INFORMATION**

### READ AND SAVE THESE INSTRUCTIONS.

Please read and understand this entire manual before attempting to assemble, operate or install the product.



- For your protection and safety, carefully read and understand the information provided in this manual completely before attempting to assemble, install or operate this product. Failure to do so could lead to fire, electrical shock or other injuries that could be hazardous or even fatal.
- DO NOT connect this fixture to an electrical system that does not provide a means for equipment grounding. Never use a fixture in a two-wire system that is not grounded. Installing a fixture into an electrical system not having a proper grounding means could cause metal parts of the fixture to carry electrical currents if any of the fixture wires, wire connections or splices were to become broken, cut or loose during the mounting or normal operation of the fixture. Under this condition, anyone coming in contact with the fixture would be subject to electrical shock, which could cause serious injury or death.

# A SAFETY INFORMATION



# **DANGER**

- DO NOT connect the bare or green insulation fixture ground wire to the black (HOT) current-carrying
  wire or the white (NEUTRAL) house wire. Connection of the bare or green fixture ground wire to the
  black or white house wires may cause metal parts of the fixture to carry electrical currents. Under
  this condition anyone coming in contact with the fixture will receive electrical shock, which could
  cause serious injury or death.
- DO NOT damage or cut the wire insulation (covering) during installation of fixture. DO NOT permit wires to contact any surface having a sharp edge. To do so may damage or cut the wire insulation, which could cause serious injury or death from electrical shock.
- If using this fixture in a DAMP location, this fixture must be connected to a supply circuit that is
  protected by a Ground Fault Circuit Interrupter (GFCI) to reduce the risk of personal injury, electrical
  shock or death.



# WARNING

- All electrical connections must be in agreement with local codes and ordinances, the National Electric Code (NEC) and ANSI/NFPA 70-1999. Contact your municipal building department to learn about your local codes, permits and/or inspections. Risk of fire most dwellings built before 1985 have supply wire rated for 140°F. Consult a qualified electrician before installation.
- To avoid personal injury, the use of gloves may be necessary while handling fixture parts with sharp edges.
- DO NOT suspend any fixture by the house wires. A fixture must always be mounted directly to an
  outlet box or to a mounting strap that is first attached to the outlet box. Wire connectors will not
  support the weight of a fixture. Suspending a fixture by the house wires and wire connectors will
  result in the fixture falling, with the possibility of personal injury and the danger of electrical shock or
  fire.
- To reduce the risk of fire, electrical shock or personal injury, wire connectors provided with this light fixture are designed to accept only one 12-gauge house wire and two lead wires from the light fixture. If your house wire is larger than 12-gauge or there is more than one house wire to connect to the corresponding fixture lead wires, consult an electrician for the proper size wire connectors to use.

#### CAUTION

- TURN OFF ELECTRICITY at main fuse box (or circuit breaker box) before beginning installation by removing the fuse (or switching the circuit breaker off).
- If you are not sure the lighting system has a grounding means, DO NOT attempt to install this fixture. Contact a qualified, licensed electrician for information regarding the proper grounding methods as required by the local electrical code in your area.
- All fixtures must be mounted to an outlet box that is supported by the building structure.
- If a dimmer control switch is used with this fixture, obtain professional advice to determine the correct type to use as well as the electrical rating required.
- Do NOT tamper with or attempt to repair LED component of fixture. The light source is designed for this specific application and should not be serviced by untrained personnel. If any servicing is required, call our customer service department.



# **PREPARATION**

Before beginning assembly of product, make sure all parts are present. Compare parts with package contents list and hardware contents list. If any part is missing or damaged, do not attempt to install, operate or assemble the product.

# **Estimated Assembly Time: 30-45 minutes**


Tools Required for Assembly (not included): Flathead Screwdriver, Phillips Screwdriver, Wire Strippers, Pliers, Wire Cutters, Safety Glasses, Stepladder, Electrical Tape

Helpful Tools (not included): A/C Tester Light, Do-It-Yourself Guide, Soft Cloth


# **ASSEMBLY INSTRUCTIONS**

1. Turn off circuit breakers and wall switch to the fixture supply line leads.

**DANGER:** Failure to disconnect power supply prior to installation may result in serious injury or death.



2. Remove existing fixture and disconnect all electrical wiring.



#### **ASSEMBLY INSTRUCTIONS**

3. Attach mounting strap (B) to outlet box (not included) using the existing washers and outlet box screws or the machine screws (BB). NOTE: If the outlet box screws required for your outlet box are of a different size than the machine screws (BB), consult with a licensed electrician before proceeding.

Tighten machine screws (BB) completely to secure mounting strap (B) to outlet box.

**A** CAUTION: Make sure the outlet box can support 35 lbs. hanging weight. Use metal outlet box; plastic outlet boxes are not recommended.

# **Hardware Used**



Machine Screw



x 2

4. If you wish to change cord length, loosen (but do *not* remove) plastic piece preassembled on cord on inside of canopy of fixture (A).

Loosen cord restraint and adjust cord to desired hanging length by pulling cord up through canopy of fixture (A) until at proper length.


Tighten cord restraint to hold cord at desired length.


**A** CAUTION: Do not overtighten cord restraint.


Move plastic piece back over opening on inside of canopy.

5. You may need to cut the excess wire to simplify the wiring. You will need at least 10 in. of wire to work with.

Prepare wire by stripping 3/4 in. of insulation from wire ends using wire strippers (not included).







PORTFOLIO. Lowes.com/portfolio


# **ASSEMBLY INSTRUCTIONS**

6. Connect BARE/GREEN ground wire from outlet box to BARE wire from mounting strap (B) using wire connector (AA). Connect clear wire with WHITE STRIPE from fixture (A) to BLACK wire from outlet box using existing wire connector or wire connector (AA). Connect CLEAR wire from fixture (A) to WHITE wire from outlet box using existing wire connector or wire connector (AA).

**NOTE:** Screw wire connectors (AA) on in a clockwise direction.

**WARNING:** Never connect BARE/GREEN ground wire to WHITE or BLACK power supply wires.

warning: To reduce the risk of fire, electrical shock or personal injury, wire connectors (AA) provided with this light fixture are designed to accept only one 12-gauge house wire and two lead wires from the light fixture. If your house wire is larger than 12-gauge or there is more than one house wire to connect to the corresponding fixture lead wires, consult an electrician for the proper size wire connectors to use.



# **Hardware Used**




Wire Connector



х3

7. Wrap electrical tape (not included) around each individual wire connector (AA) down to the wire.


**WARNING:** Make sure no bare wire or wire strands are visible after making connections.



### **ASSEMBLY INSTRUCTIONS**

8. Carefully arrange excess wiring and wire connectors (AA) within canopy at top of fixture (A).

Align holes in edge of canopy with screw holes at ends of mounting strap (B). Secure fixture (A) with mounting strap screws (CC).



9. Remove socket ring (C) from the socket on fixture (A).

**CAUTION:** Be very careful when removing socket ring (C) so as not to break the preassembled bulb cover.


Slide glass shade (sold separately) very carefully over the bulb cover on fixture (A). Secure with socket ring (C).


**CAUTION:** Do not overtighten socket ring (C) as glass may crack or break.

**CAUTION:** Be very careful when installing glass shade and socket ring (C) as the bulb cover may crack or break.

10. Restore power and test fixture (A).

If light does not function, please refer to TROUBLESHOOTING below.





#### **CARE AND MAINTENANCE**

- Shut off main power supply. Wipe fixture with soft, damp cloth. Use window cleaner to clean glass. Do not use an abrasive cleaner on glass or fixture.
- Total wattage for this fixture is 7 watts; do not attempt to replace the LEDs.

# **TROUBLESHOOTING**

**MARNING:** Before beginning work, shut off the power supply to avoid electrical shock.

PROBLEM	POSSIBLE CAUSE	CORRECTIVE ACTION
Light does not come on initially or no longer comes on.	<ol> <li>Power is OFF.</li> <li>Faulty connection.</li> <li>LED component is not working properly.</li> </ol>	<ol> <li>Make sure power supply is ON.</li> <li>Check wiring and all connections.</li> <li>Contact customer service.</li> </ol>
Fuse blows out or circuit breaker trips.	<ol> <li>Crossed wires.</li> <li>Power wire is grounding out.</li> </ol>	<ol> <li>Check wiring.</li> <li>Check all connections.</li> </ol>

### **WARRANTY**

The distributor warrants all of its lighting fixtures against defects in materials and workmanship for five (5) years from the date of purchase. If within this period the product is found to be defective, take a copy of the bill of sale as a proof of purchase and the product in its original carton to the place of purchase. The distributor will, at its option, repair, replace or refund the purchase price to the consumer. All costs of installation and removal of the fixture is the responsibility of the consumer. This warranty does not cover fixtures becoming defective due to misuse, accidental damage or improper handling and/or installation and specifically excludes liability for direct, incidental or consequential damages. As some states do not allow exclusions of limitations on an implied warranty, the above exclusion and limitation may not apply. This warranty gives you specific rights and you may also have other rights which may vary from state to state.

8

Printed In China



KHLI1512