

To be sold only with installation instructions.

Instructions

Crimp with IDEAL Electrician's Pliers, models 430 or 420; IDEAL Crimp Tool, model 425 (using small crimp die) or model 429 using "BARE" crimp die). Insulate with IDEAL model 417 WRAP-CAP®.

Note: Always turn off power before installing or removing connectors.

Listed as a PRESSURE-TYPE wire connector on the following solid and/or stranded wire combinations: COPPER TO COPPER ONLY (DO NOT USE ON ALUMINUM).

1. Strip 2" & insert wires.




3. Crimp sleeve twice & trim.



2. Pretwist wires before crimping.



4. Apply WRAP-CAP® insulator.



Model 411 Sleeve with WRAP-CAP® - 600V listing applies*

2 #8**

2 or 3 #10

4 #10 Sol.

3 to 5 #12

5 #14

1 #8 w/1 or 2 #10

1 #8 w/1 to 3 #12

1 #8 w/1 to 4 #14

2 #10 w/1 to 3 #18

3 #10 w/1 #12

3 #10 w/1 or 2 #14

3 #10 w/1 or 2 #16

3 #10 w/1 or 2 #18

1 #12 w/4 #14

2 #12 w/2 or 3 #14

2 #8 w/1 #12

2 #8 w/1 or 2 #14

1 #10 w/2 to 4 #12

1 #10 w/3 or 4 #14

1 #10 w/4 #16

2 #10 w/1 to 3 #12

2 #10 w/1 to 3 #14

2 #10 w/1 to 3 #16

2 #12 w/3 #16

3 #12 w/1 or 2 #14

3 #12 w/1 or 2 #16

3 #12 w/1 or 2 #18

4 #12 w/1 #14

4 #12 w/1 #16

4 #12 w/1 #18

*1000V Max. in fixtures and signs.

**Not C.S.A. certified.

OEM: A connector designated as an OEM (Original Equipment Manufacturer) connector does not require pre-twisting when used in OEM applications.