







IMPORTANT: Read all instructions before installing plate. Retain for future reference.

SAFETY: Turn the power off at main fuse / breaker panel before attempting any electrical work. This luminaire must be wired in accordance with local electrical codes and ordinances. Grounding connections should be done in the detachable junction box.

WARNING: Make sure the power is OFF from the electrical panel before starting installation or attempting any maintenance. Indoor installation only.

INSTALLATION:

1. Nail-in the mounting plate to the ceiling joist. Measure the position of the opening on the mounting plate from each wall [Fig. 1].
2. Pull the supply wire through the cut-out hole. Do the electrical supply connection in the detachable junction box (**Note:** A licensed electrician must do the connections as per the local electrical code). Insert the junction box into the ceiling.
3. A) Secure the junction box by attaching it to the snap in clips on the plate [Fig. 2A].
B) Secure vertical junction boxes to plate using captive fasteners [Fig. 2B].
4. Install the drywall on to the ceiling [Fig. 3].
5. Cut-out a circle where the mounting plate opening is located [Fig. 4].
6. Do the connection to the luminaire with the DC 2.1 connector [Fig. 5].

7. Push the spring clips upwards and push the luminaire into the cut hole of the ceiling. Release the spring clips and align the luminaire to sit properly over the ceiling cut hole [Fig. 6].
8. Switch on the supply breaker and turn on the luminaire.

IMPORTANTE: Lea todas las instrucciones antes de instalar la placa. Retener para referencia futura.

SEGURIDAD: Apague la energía en el panel principal de fusibles / disyuntores antes de intentar cualquier trabajo eléctrico. Esta luminaria debe estar cableada de acuerdo con los códigos y ordenanzas eléctricos locales. Las conexiones a tierra deben hacerse en la caja de conexiones desmontable.

ADVERTENCIA: Asegúrese de que el panel eléctrico esté APAGADO antes de comenzar la instalación o intentar cualquier mantenimiento. Sólo para instalaciones interiores.

INSTALACIÓN:

1. Clava la placa de montaje a la viga del techo. Mida la posición de la abertura en la placa de montaje desde cada pared [Fig. 1].
2. Tire del cable de suministro a través del orificio recortado. Realice la conexión de suministro eléctrico en la caja de conexiones desmontable (**Nota:** Un electricista certificado debe hacer las conexiones según el código eléctrico local). Inserte la caja de conexiones en el techo.
3. A) Asegure la caja de conexiones uniéndola a los clips a presión en la placa [Fig. 2A].
B) Asegure las cajas de conexiones verticales a la placa usando afianzadores cautivos [Fig. 2B].

Hole Cut Size / Tamaño de Orificio
TL6020U 6¼" (160mm)

4. Instale el panel de yeso en el techo [Fig. 3].
5. Recorte un círculo donde se encuentra la abertura de la placa de montaje [Fig. 4].
6. Realice la conexión a la luminaria con el conector DC 2.1 [Fig. 5].
7. Empuje los clips de resorte hacia arriba y empuje la luminaria dentro del agujero del techo. Suelte los clips de resorte y alinee la luminaria para que descansen correctamente sobre el orificio del techo [Fig. 6].
8. Restablece la energía y enciende la luminaria.