

| April 26, 2023 | 6733D Triac/Forward Phase-cut dimmers | | | | | | | |
|---------------------|---------------------------------------|-------------------------------|----------------------------------|--------------------------------------|--------------------------|---|--|---------------|
| Brand | Series | Model # | Wiring | watts | dimming method | Max # of Luminaires | Notes | dimming range |
| Lutron | Ariadni/Toggler LED+ | AYCL-153P | Single-pole/3-way | 150 | Toggler | 18 | 3-Way only works with a 3-Way switch | 0% - 100% |
| | | TGCL-153P | | | slide with ON/OFF button | | | |
| | Diva LED+ | DVCL-153P | | | | | | |
| | Skylark LED+ | SCL-153P | | | | | | |
| | Skylark Contour LED+ | CTCL-153P | | | | | | |
| | Lumea LED+ | LGCL-153P | | | | | | |
| | Maestro LED+ | MACL-153M | Single-pole/3-way/multi-location | 150 | Touch | 18 | 3-Way only works with a 3-Way switch or dimmer companion MA-R (not a dimmer). Multi-location only work with MA-R | 0% - 98% |
| | Sunnata | STCL-153P | Single-pole/3-way | 3-Way only works with a 3-Way switch | | | | |
| Caseta | PD-6WCL | Single-pole or multi-location | 150 | Touch and Wireless | 18 | Multi-location only works with Pico wireless remote PJ2, Amazon alexa, Google Assistant, Apple HomeKit, Apple Watch | 0% - 96% | |
| Leviton | Decora | DSL06 | Single-pole/3-Way | 300 | Rocker with Slide Bar | 37 | 3-Way only works with a 3-Way switch | 0% - 103% |
| | Trimatron | RNL06 | Single-pole | 150 | Rotary | 18 | | 0% - 102% |
| | Decora Smart | DW1KD | Single-pole/3-Way | 450 | Touch and Wi-Fi | 56 | 3-Way only works with remote DDOOR Requires neutral wire connection | 2% - 90% |
| | Sureslide | 6674 | Single-pole/3-Way | 150 | slide with ON/OFF button | 18 | 3-Way only works with a 3-Way switch | 8% - 101% |
| Legrand | Radiant | RHCL453 | Single-pole/3-Way | 450 | slide with ON/OFF button | 56 | 3-Way only works with a 3-Way switch | 0% - 102% |
| Commercial Electric | Smart Dimmer With Motion Sensor | 1006456159 | Single-pole | 150 | Touch and Wi-Fi | 18 | | 0% - 100% |

