

AFCI AND GFCI

Homeowner's Guide

How to keep you, your family, and your possessions safe **usa.siemens.com/afci**



Congratulations on the purchase of your new home.

This guide will help you understand the importance of arc fault circuit interrupters (AFCIs) and ground fault circuit interrupters (GFCIs) that are located in your load center. For over 160 years, Siemens has produced excellent performing electrical products in the market that provide increased levels of safety. With its long history of engineering and innovation, AFCIs and GFCIs are examples of how Siemens implements advanced technology to ensure the well-being of individuals. This technology is thoroughly tested to guarantee performance and reliability.

How do AFCIs and GFCIs protect my family?

AFCIs and GFCIs will shut down, or trip, a branch circuit when certain conditions have been met. Unlike typical thermal magnetic circuit breakers, AFCIs monitor the circuit for arc faults, an unintentional electrical discharge that ignite surrounding materials like wood or insulation. Arc faults are difficult to detect because they are often intermittent and occur in hidden locations, such as behind drywall and in the attic. AFCIs search for arcing conditions before tragedy strikes.



GFCIs protect against electrical shock that result from ground faults. Ground faults occur when electrical current in devices stray outside of its normal path. A human body can become part of this circuit, which results in an electrical shock. GFCIs analyze the amount of current entering and exiting from the circuit and will trip when the difference is greater than a certain value.

Dual Function Circuit Breaker

combines GFCI and AFCI, protecting against both Arc Faults and Ground Faults. This, along with the new Self Test & Lockout feature, makes it the first in class in electrical safety for homeowners. The new Self Test and Lockout feature enables the breaker to automatically and continuously test itself to ensure it is working properly. If it detected that the device has been compromised, the device trips itself and locks out the homeowner from resetting the device. This effortless system guarantees that only the best protection is given to your home at all times.

Where can arc faults occur? Arc faults can occur from the following conditions:



Damaged power supply cord



Damaged wiring



Pierced wiring



Negligence

National Electrical Code Adoption Effective February 2024



U.S. Territory Adoption

American Samoa - 2017 NEC Guam - 2008 NEC Puerto Rico[‡] - 2017 NEC Northern Mariana - 2008 NEC U.S. Virgin Islands - 2017 NEC

State Adoption Legend

- 2023 National Electrical Code
- 2020 National Electrical Code
- 2017 National Electrical Code
- 2014 National Electrical Code
- 2011 National Electrical Code
- 2008 National Electrical Code
- No Statewide Adoption

*Also subject to local adoption

* With state or city amendments

*Commercial adoption, residential dwellings on older code

Reduce chances of an arc fault occuring in your home

What more can I do to reduce the chances of an arc fault?

There are several preventive factors that homeowners can take in order to decrease the chance of an arc fault occurring.

- All connections between the light socket and the light bulb base should be tight. An arc can occur in a loose connection, which will cause the AFCI breaker to trip.
- Beware that the circuit is not overloaded with an excessive amount of electronics. The breaker is
- only able to support a specified amount of wattage, and if exceeded, the breaker will trip.
- Make sure furniture is not on or pushing against electrical wires.
- All devices in the home should be Underwriters Laboratories (UL) listed, or equivalent, and comply with part 15 of the FCC regulations, or they could possibly cause the AFCI to trip.
- Always use a qualified, licensed electrician for wiring electrical projects.
- If any blackened plugs, damaged wires, or noisy circuit breakers are discovered, an electrical problem has occurred and the homeowner should call an electrician.
- It is also suggested to protect electronics with high quality surge protectors. Surge protectors protect the electronics from times of high electrical surges, like thunderstorms.







Did you know?

From 2013-2017, fires caused by electrical distribution or lighting equipment was the leading cause of home fire property damage. An average of 35,000 such fires caused 500 deaths, 1,130 injuries and \$1.4 billion in direct property damage per year. AFCIs help prevent such fires.

Since the first introduction of GFCIs in homes, there has been an 81% drop in electrocutions and 95% drop in electrocutions from consumer products.

Source: "Home Structure Fires" National Fire Protection Association, October 2019 www.esfi.org

LED Trip Indicators

LED indicator	Last known trip condition	P 2 0
Off	Overcurrent or Short Circuit	
On	Arc or Arc-to-ground fault	LED Test
		button

LED indicators			LEFP A	
1	2	Last known trip condition		
Off	Off	Overcurrent or Short Circuit	LED 1 Test	
On	Off	Arc or Arc-to-ground fault (leg A)	LED 2 butto	ns
Off	On	Arc or Arc-to-ground fault (leg B)		

There are "testers" marketed to test the functionality of AFCIs and GFCIs, but they are not endorsed by either the Underwriters Laboratories (UL) or National Electrical Manufacturers Association (NEMA) because the "testers" do not create genuine arcing conditions. The only way to properly test an AFCI or GFCI is to use the "Push-to-Test" button located on the device. It is recommended by UL to test all AFCIs and GFCIs monthly to ensure the device is working correctly.

What happens if a breaker trips?

A breaker will trip if a problem within the branch circuit occurred. The homeowner should not perform the troubleshooting required to fix the problem, but by using the LED indicator technology on all AFCIs, the homeowner can inform the electrician the reason the breaker tripped.

Regardless of whether the breaker is an AFCI or GFCI, in order to turn it back on after being tripped, first flip the handle from the "TRIPPED" position to the "OFF" position. Then, flip the handle to the "ON" position. If the breaker is an AFCI, the LED indicators will inform the condition of the last trip. The figure on the next page displays the trip condition depending on the LEDs illuminated. The fault stays in the memory of the AFCI for 30 days.

The last known trip conditions can be cleared by the following process for both 1- and 2-pole breakers.

- 1. Turn the AFCI to the "OFF" position.
- 2. Press and hold the blue Push-to-Test button(s).
- 3. Turn the AFCI to the "ON" position.
- 4. Release the Push-to-Test button(s) within 3 seconds.



Operating handle positions

6

National Electrical Code[®] Progression

The need for AFCI has been established by various respected organizations. Requirements are already in place to mandate the use of the Combination Type AFCI. These Combination Type AFCIs provide the maximum protection available today for reducing the possibly catastrophic effects of arcing faults.

1999 NEC®

- Listed AFCI future requirement in Code - Allows Branch/Feeder AFCI
- January 1, 2002: bedroom receptacles

2002 NEC®

- Listed AFCI in ALL bedroom circuits
 - Allows Branch/Feeder AFCI

2005 NEC®

- Combination Type AFCI in bedroom circuits
- Branch/Feeder AFCI permitted until January 1, 2008

2008 NEC®

- Combination Type AFCI
- Expand to 1 pole, 15-20A circuits installed in bedrooms, family rooms, living rooms, parlors, libraries, dens, sunrooms, recreation rooms, closets or similar rooms.



2011 NEC®

- Combination Type AFCI
- 1 15-20A circuits installed in family rooms, dining rooms, living rooms, parlors, libraries, dens, bedrooms, sunrooms, recreation rooms, closets, hallways, or similar rooms or areas.

2014 NEC®

- Combination Type AFCI and Dual Function AFCI/GFCI
- All 120-volt, single-phase, 15-20A branch circuits supplying outlets or devices installed in dwelling unit kitchens, family rooms, dining rooms, living rooms, parlors, libraries, dens, bedrooms, sunrooms, recreation rooms, closets, hallways, laundry areas or similar rooms or areas.

2017 NEC®

- Combination Type AFCI and Dual Function AFCI/GFCI
- Same as 2014 and expanded to guest rooms and guest suites in hotels and motels as well as dormitory units.

2020 NEC®

- Combination Type AFCI and Dual Function AFCI/GFCI
- Same as 2017 and expanded to patient sleeping rooms in nursing homes and limited-care facilities

2023 NEC®

- Combination Type AFCI and Dual Function AFCI/GFCI
- Same as 2020 and expanded to areas designed for use exclusively as sleeping quarters in fire stations, police stations, ambulance stations, rescue stations, ranger stations, and similar locations.

Legal Manufacturer

Siemens Industry, Inc. 3617 Parkway Ln Peachtree Corners, GA 30092 United States of America Telephone: +1 (800) 333-7421 www.usa.siemens.com/afci Order No. RPBR-HOME1-0324 This document contains a general description of available technical options only, and its effectiveness will be subject to specific variables including field conditions and project parameters. Siemens does not make representations, warranties, or assurances as to the accuracy or completeness of the content contained herein. Siemens reserves the right to modify the technology and product specifications in its sole discretion without advance notice.