








USE AND CARE MANUAL

5 LIGHT PENDANT



Hardware (Parts are not to scale)

H1 Mounting bracket (Pre-assembled to canopy assembly (A)) 1 pc		H2 Support screw (Pre-assembled to mounting bracket (H1)) 2 pcs		H3 Outlet box screw 2 pcs	
H4 Green ground screw (Pre-assembled to mounting bracket (H1)) 1 pc		H5 Wire connector 3 pcs		H6 Decoration tube 1 pc	

**THIS MANUAL CONTAINS IMPORTANT SAFETY INFORMATION. PLEASE READ AND
KEEP FOR FUTURE REFERENCE.**

IMPORTANT SAFETY INFORMATION

- Please read and understand this entire manual before attempting to assemble, operate or install the product.
 - Turn off electricity at main fuse box (or circuit breaker box) before beginning installation by removing fuse (or switching off circuit breaker).
 - Be careful not to damage or cut the wire insulation (covering) during fixture installation. Do not permit wires to contact any surface having a sharp edge. To do so may damage or cut the wire insulation, which could cause serious injury or death from electric shock.
 - All electrical connections must be in agreement with local codes, ordinances or the national electric code (NEC). Contact your municipal building department to learn about your local codes, permits and/or inspections. If you do not have electrical wiring experience, refer to a do-it-yourself wiring handbook or have your fixture installed by a qualified licensed electrician.
 - Risk of fire – most dwellings built before 1985 have supply wire rated for 140°F/60°C. Consult a qualified electrician before installation.
 - Do not exceed the recommended wattage. Refer to the re-lamping label on the light socket for maximum wattage.
 - Do not replace a bulb when electrical outlet switch is turned to the “ON” position.
 - Do not immerse your lamp in water; doing so will damage the wire.
 - Keep materials that burn easily away from lighted bulbs.
-


PREPARATION

- Before beginning assembly, installation or operation of product, make sure all parts are present. Compare parts with package contents list and diagram on the previous page. If any part is missing or damaged, do not attempt to assemble, install or operate the product. Contact customer service for replacement parts.
 - Tools required for assembly (not included): flathead screwdriver, phillips screwdriver, pliers, electrical tape, wire cutters, safety glasses, ladder, wire stripper.
-

INSTALLATION


1 Preparing the mounting bracket

- Unscrew the two support screws (H2) from the mounting bracket (H1). Remove the mounting bracket (H1) from the canopy (A), and keep the support screws (H2) for later use.



2 Installing the mounting bracket


- Fasten the mounting bracket (H1) onto the outlet box (not provided) using two outlet box screws (H3).



INSTALLATION (continued)



3 Assembling the fixture body

- Press the wires of the socket assemblies (H) into the hole of the fixture body (F) and tighten the socket assemblies (H) into the fixture body (F) as shown in the diagram.
- Tighten the ball assemblies (G) into the hole of the fixture body (F) as shown in the diagram.



4 Assembling the tubes and canopy assembly to the fixture body

- Guide the fixture wire with the bare copper ground wire through the tubes (B, C, D) and the canopy assembly (A).
- Tighten the canopy assembly (A) and the tubes (B, C, D) together onto the fixture body (F) until secured respectively as shown in the diagram.
- Tighten the decoration tube (H6) to the bottom of the fixture body (F).
- There are seven different height options for the user to choose from:




INSTALLATION (continued)

5 Making the electrical connections

- Strip 3/4 in. of insulation from the wire ends.
- Connect the black wire from the fixture to the black wire from the outlet box, then connect the white wire from the fixture to the white wire from the outlet box.
- The bare copper ground wire from the fixture body (F) must loop one turn under the head of the green ground screw (H4) on the mounting bracket (H1) before it is connected to the ground conductor of the supply circuit.
- Cover the wires with wire connectors (H5). Tape the wire connectors (H5) and wires together, and carefully position all wires inside the outlet box.


NOTE: Do not let go of the canopy assembly (A) before the canopy assembly (A) is installed on the mounting bracket (H1).



6 Assembling the canopy assembly to the outlet box

- Place the canopy assembly (A) over the outlet box, align the two holes of the mounting bracket (H1) and the canopy of the canopy assembly (A), then tighten the support screws (H2).


NOTE: Do not let go of the canopy assembly (A) before the canopy assembly (A) is installed on the mounting bracket (H1).



7 Installing the light bulbs

- Install the light bulbs (not provided) into the sockets. Use five **40 W candelabra base (E12) type "B"** bulbs (recommended).


Note: You can also use five **9W candelabra base (E12) self-ballasted LED type "B"** bulbs. Do not exceed the recommended wattage.



INSTALLATION (continued)

8 Installing the glass shades

- Place the glass shades (E) over the socket of the socket assembly (H), tighten the glass shades (E) on the socket assembly (H) (do not over tighten) as shown in the diagram.



CLEANING

- Do not use any cleaners with chemicals, solvents, or harsh abrasives. Use only a dry, soft cloth to dust or wipe carefully.
- To clean the fixture, disconnect the power by turning off the circuit breaker or by removing the fuse at the fuse box. Use a dry or slightly dampened, clean cloth to wipe the exterior surface of the fixture.

TROUBLESHOOTING

- The light does not come on at all:
 - a) Check whether the bulbs were burned out.
 - b) Make sure the wall switch is on.
 - c) Make sure the wiring is correct.
 - d) Make sure the circuit breaker is set in the "ON" position.
- Fuse blows or circuit trips when light is turned on.
 - a) Check for crossed wires, ensure wiring is correct.