

**5CCT**  
SELECTABLE

2700K  
3000K  
3500K  
4000K  
5000K



## 5CCT LED Recessed Light With Night Light

### RECESSED LIGHTS

Input Voltage	AC120V 60Hz
Input Power	9W + 3W
CCT	5CCT + 2000K
LED Type	2835/SMD
Lumens	720lm - 810lm
CRI	80-85
PFC	>50%
Material	PS, aluminum



### SAFETY INSTRUCTIONS

Recessed lighting is certified by ETL & FCC & Energy Star(except for 5CCT )of a high standard. This canless LED recessed light is IC rated , with more convenient and secure UL connectors. But to reduce the risk of death, personal injury, or property damage from fire, electric shock, and other hazards, please read all warnings and instructions included with and on the fixture box and all fixture labels, please review instructions carefully before proceeding

#### WARNING

##### RISK OF ELECTRIC SHOCK

- ⚠ All electrical connections must be in accordance with local and National Electric Code(N.E.C.) standards.
- ⚠ Consult a qualified electrician if you are unfamiliar with proper electrical wiring connections.
- ⚠ Turn off the switch and circuit breaker before installing this LED light.
- ⚠ Do not alter, re-locate or remove wiring.
- ⚠ Double-check all connections to be sure they are tight and correct.
- ⚠ Verify that the supply voltage is correct by comparing it with the luminaire label information.

##### RISK OF FIRE

- ⚠ Keep combustibles and other materials that may burn away from lights.
- ⚠ The maximum ambient temperature is 104°F. Do not operate the fixture at temperatures higher than it.

### HOW TO SWITCH THE MODE

Flip the wall switch ON-OFF-ON within 2 seconds to change the mode.



Light "On" in  
Downlight Mode



Turn Off the Light  
within 2s



Turn "On" Again within  
2s to Switch to  
Night Light Mode

**NOTE:** The light will return to Downlight Mode by default after being turned off for over 8 seconds.

#### IMPORTANT

- ▶ Our color temperature has been strictly monitored. But the color temperature will be slightly different with varied monitors. Please test them before installation on the ceiling wall and see the color if it meets your needs.
- ▶ **SAVE THESE INSTRUCTIONS** For safest operation, read and become familiar with complete installation instructions prior to use. Pay close attention to this manual and stay within its guidelines when using this product.

#### ROUTINE MAINTENANCE

- ▶ Please make sure the power is off before maintenance
- ▶ To avoid any damage to the product, please do not use any chemical solvents during routine maintenance
- ▶ To ensure better lighting, please clean the lamp at regular intervals.


#### CAUTION

All parts must be used as indicated in this manual. Do not substitute any parts, leave parts out, or use parts that are worn out or broken. Failure to obey this instruction could invalidate the ETL certification.


### STEP-BY-STEP INSTALLATION

**TOOLS REQUIRED** Saw, Ladder, Measuring Tape, Electrical Wiring (The wire should be AWG14-18 for application to connect the fixture), Safety glasses and gloves.


**Notice** After the removal of the knockouts (about 0.86-inch diameter) in step No. 2, additional cable connectors are needed to secure the wires passing through the knockouts. You could buy the cable connectors as per your need.




1  
Cut a hole in the ceiling  
with a saw



2  
Carefully remove the knot-out  
with a screw driver or punch



3  
Open the conjunction boxes  
cover and connect the wires



4  
Set the CCT ( 2700K/3000K/  
3500K/4000K/5000K)



5  
Connect the fixture light Put the  
conjunction boxes into the ceiling



6  
Push up the spring clips and the  
push the light into the ceiling