



Electrical Installation

Please confirm that you have all parts to your system before starting installation.

Below image shows how to connect the solar panel to the 12 Volt batteries

Step1 Cover the panel with card board, cloth, or a similar option so there are no output power

Step2 Connect the charge controller to the solar panel

Step3 Connect the battery clamps to the charge controller

Step4 Connect the battery clamps to the battery in parallel. Parallel connections = Positive to Positive and Negative to Negative

Step5 Remove the cover from solar panel



When installing solar panels configuration and systems, please carefully observe correct cable connections and polarity. The solar panels can be damaged by not observing the correct electrical installation and polarity; in addition, this will void the warranty of your solar panels. Having a multi-meter handy will help to confirm correct polarities.

Extending the wiring

If you choose to mount your solar panel further away from the charge controller by extending the wiring we recommend the following gauges at each specified distance. Use stranded wire instead of solid wire. Stranded wire does not fatigue or loose connections over time.

Appropriate wire gauge should be used for distance and total amperage, for further information please consult with a licensed electrician or through an online wiring chart calculator

To prevent loss of current we suggest mounting the solar panel within 20 feet of the charge controller and the charge controller should be installed within 5 feet of the battery.