

September 15, 2020	1416C3C Triac/Forward Phase-cut dimmers										
Brand	Type	Series	Model #	Wiring	watts	dimming method	Version Code	Max # of Luminaires	Notes	minimum dimming range	
Lutron	C.L	Ariadni/Toggler C.L	AYCL-153P	Single-pole/3-way	150	Toggler	T8, T9	3	3-Way only works with a 3-Way switch	0%	
			TGCL-153P								
			Diva C.L			DVCL-153P					
			Skylark C.L			SCL-153P					
			Skylark Contour C.L			CTCL-153P					
		Lumea C.L	LGCL-153P								
		Maestro C.L	MACL-153M	Single-pole/3-way/ multi-location	150	Digital	2014	3	3-Way only works with a 3-Way switch or dimmer companion MA-R (not a dimmer). Multi-location only work with MA-R	0%	
			MSCL-VP153M	Single-pole/3-way/ multi-location	150	Digital/Vacancy Sensor	T2	3	3-Way only works with a 3-Way switch or dimmer companion MA-R (not a dimmer). Multi-location only work with MA-R	0%	
			MSCL-OP153M	Digital/Occupancy Sensor							
			MRF2-6CL	Single-pole/3-way/ multi-location	150	Digital and Wireless	M6	3	3-Way or multi-location only works with companion MA-R (not a dimmer)	0%	
Nova T	NTCL-250	Single-pole	250	slide to off	BR Y02	6		0%			
RF C.L	Grafik T	GT-150	Single-pole/3-way/ multi-location	150	Digital	T6	3	3-Way or multi-location only works with companion GT-AD (not a dimmer)	0%		
	Grafik T RF	GTJ 150				M6			0%		
	Wireless	Caseta	PD-6WCL	Single-pole or multi-location	150	Digital and Wireless,	SD11	3	Multi-location only works with Pico wireless remote PJ2, amazon alexa, Google Assistant, Apple HomeKit, Apple Watch	0%	
Leviton	Universal Dimmer	Decora	DSL06-1L	Single-pole/3-Way	300	slide with ON/OFF button	NA	7	3-Way only works with a 3-Way switch	10%	
		Illuma Tech	IPL06-10	Single-pole/3-Way	150	slide with ON/OFF button	NA	3	3-Way only works with a 3-Way switch	0%	
		Sureslide	6672-1L	single	150	slide to off	NA	3		0%	
		Sureslide	6674-P0	Single-pole/3-Way	150	slide with ON/OFF button	NA	3	3-Way only works with a 3-Way switch	0%	
		Renu	REL06	Single-pole/3-Way	300	Digital	NA	7	3-Way only works with remote RE00R Requires neutral wire connection	0%	
		Decora Digital	DDMX1-BL	Single-pole/3-Way	450	Digital or Bluetooth	NA	11	3-Way only works with remote DDOOR-DL Requires neutral wire connection	0%	

