

September 8, 2016	61431B/RB6WHWH9T14xx Triac/Phase-cut dimmers									
Brand	Type	Series	Model #	Wiring	watts	dimming method	Version Code	Max # of Luminaires	Notes	dimming range
Lutron	C.L	Ariadni/Toggler C.L	AYCL-153P	Single-pole/3-way	150	Toggler	T8, T9	7	3-Way only works with a 3-Way switch	4% - 100%
			TGCL-153P			slide with ON/OFF button				
		Diva C.L	DVCL-153P							
		Skylark C.L	SCL-153P							
		Skylark Contour C.L	CTCL-153P							
		Lumea C.L	LGCL-153P							
		Maestro C.L	MACL-153M	Single-pole/3-way/ multi-location	150	Digital	2014	7	3-Way only works with a 3-Way switch or dimmer companion MA-R (not a dimmer). Multi-location only work with MA-R	6% - 96%
			MSCL-VP153M	Single-pole/3-way/ multi-location	150	Digital/Vacancy Sensor	T2	7	3-Way only works with a 3-Way switch or dimmer companion MA-R (not a dimmer). Multi-location only work with MA-R	5% - 97%
			MSCL-OP153M	Digital/Occupancy Sensor						
			MRF2-6CL	Single-pole/3-way/ multi-location	150	Digital and Wireless	M6	7	3-Way or multi-location only works with companion MA-R (not a dimmer)	6% - 98%
		Nova T	NTCL-250	Single-pole	250	slide to off	BR Y02	11		6% - 100%
		Grafik T	GT-150	Single-pole/3-way/ multi-location	150	Digital	T6	7	3-Way or multi-location only works with companion GT-AD (not a dimmer)	5% - 100%
Grafik T RF	GTJ-150		M6				5% - 100%			
Wireless	Caseta	PD-6WCL	Single-pole or multi-location	150	Digital and Wireless	SD11	7	Multi-location only works with Pico wireless remote PJ2	3% - 98%	
Leviton	Universal Dimmer	Decora	DSL06-1L	Single-pole/3-Way	300	slide with ON/OFF button	NA	14	3-Way only works with a 3-Way switch	25% - 100%
		Illuma Tech	IPL06-10	Single-pole/3-Way	150	slide with ON/OFF button	NA	7	3-Way only works with a 3-Way switch	5% - 100%
		Sureslide	6672-1L	single	150	slide to off	NA	7		19% - 100%
		Sureslide	6674-P0	Single-pole/3-Way	150	slide with ON/OFF button	NA	7	3-Way only works with a 3-Way switch	5% - 100%
		Renu	REL06	Single-pole/3-Way	300	Digital	NA	14	3-Way only works with remote RE00R Requires neutral wire connection	13% - 100%
		Decora Digital	DDMX1-BL	Single-pole/3-Way	450	Digital or Bluetooth	NA	21	3-Way only works with remote DDOOR-DL Requires neutral wire connection	9% - 100%

