

Part List and Hardware List

1

A

B

C

D

E

F

G

H

I

2

P

Q

R

black

P white

Q Earth wire

R

3

(not included)

Step 2: 1) Connect all fixture wires to the household wires: black to black (Live/P); white to white (Neutral/Q); ground wire to ground(R). Then secure all connections with wire connectors .

2) Use M4 nuts (D) to secure the ceiling plate, then connect the hanging chain between it and the assembled fixture.

Step 3: 1) Install 4 pieces of E12 bulb (not included).

2) Finished Installation.

Maximum bulb wattage: 25W Max

3) Attach the decorative wire rack (F) to the lampshade (G).

2) INSPECT all parts. Do NOT install and contact us via Message if any are missing or damaged.