

Project:

Fixture Type: Location:

Contact:

One-light Bath

Wall mounted • Damp location listed PROGRESS LED



P300243-009-30

Images:

This LED bath light offers a taste of subtle sophistication to any design. Beautiful brushed nickel bands cap each end of the shade for a clean, modern aesthetic. The shade includes an integrated 23w LED bulb.

Specifications:

Description:

- Brushed Nickel (-009)
- Steel Construction
- White PMMA diffuser
- · This LED bath light offers a taste of subtle sophistication to any design.
- Beautiful brushed nickel bands cap each end of the shade for a clean, modern aesthetic.
- 1798 delivered lumens.
- Ideal for any bathroom.
- Perfect for any modern, luxury, or transitional settings.
- Measures 24-inch width by 5-15/16-inch height.
- Uses one LED bulb that is included (24.3w max).
- Able to be fully dimmable with dimmable bulbs.
- Includes installation instructions and mounting hardware.
- Progress Lighting products are designed for exceptional quality, reliability, and functionality.
- Mounting Backplate for outlet box included
- 6" of wire supplied
- ENERGY STAR[®] qualified
- Meets California Title 24 JA8-2016

Performance:

Number of Modules	1	
Input Power	24.3w	
Input Voltage	120 V	
Input Frequency	60 Hz	
Lumens/LPW (Delivered)	1923/79.1 (LM-79)	
ССТ		
CRI	90 CRI	
Life (hours)	50,000 (L70/TM-21)	
FCC	Meets FCC Title 47, Part 15 Class B	
Min. Start Temp	-30 °C	
Warranty	5-year Limited Warranty	
Labels	cETLus Damp location listed	
	ENERGY STAR [®] qualified	
	Meets California Title 24 JA8-2016	



Dimensions:

Width: 24" Depth: 4-3/16" Height: 5-15/16"



One-light Bath

Wall mounted • Damp location listed PROGRESS LED



P300243-009-30

Dimming Notes:

P300243 is designed to be compatible with many Triac/ELV controls.

The following is a partial list of known compatible dimmer controls.

Dimming Controls

IDevices IDEV009
Leviton 6672
Lutron DVELV-300P
Lutron DVCL-253P
Lutron Caseta Wireless
Lutron AYCL-153P
Lutron SCL-153P
Lutron TGCL-153-PH-WH

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.