



37" HD Sound bar with Bluetooth Wireless User's Guide for Model ITB259 v2913-01 For the most up-to-date version of this User's Guide, go to: www.iLiveElectronics.com

Safety Instructions & Warnings



WARNING: To reduce the risk of electric shock, do not remove cover (or back). No user-serviceable parts inside. Refer servicing to qualified service personnel.



The exclamation point within an equilateral triangle is intended to alert the user to the presence of important operating and maintenance (servicing) instructions in the literature accompanying the appliance.



The lightning flash with arrowhead symbol, within an equilateral triangle, is intended to alert the user to the presence of uninsulated "dangerous voltage" within the product's enclosure that may be of sufficient magnitude to constitute a risk of electric shock to persons.



This symbol indicates that this product incorporates double insulation between hazardous mains voltage and user accessible parts.

WARNING: DO NOT INGEST BATTERY, CHEMICAL BURN HAZARD.



WARNING: This product can expose you to chemicals including lead, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings, ca.gov. This product meets and complies with required Federal product guidelines

Important Safety Instructions

- Read these Instructions.
- Keep these Instructions.
- Heed all Warnings.
- Follow all instructions.
- Do not use this apparatus near water.
- Clean only with a dry cloth.
- Do not block any ventilation openings. Install in accordance with the manufacturer's instructions.
- Do not install near any heat sources such as radiators, heat registers, stoves, or other apparatus (including amplifiers) that produce heat.
- Do not defeat the safety purpose of the polarized or grounding - type plug. A polarized plug has two blades with one wider than the other. A grounding type plug has two blades and a third grounding prong. The wide blade or the third prong are provided for your safety. When the provided plug does not fit into your outlet, consult an electrician for replacement of the obsolete outlet.
- Protect the power cord from being walked on or pinched particularly at plugs, convenience receptacles, and the point where they exit from the apparatus.
- Only use attachments/accessories specified by the manufacturer.
- Unplug this apparatus during lightning storms or when unused for long periods of time.
- Refer all servicing to qualified service personnel. Servicing is required when the apparatus has been damaged in any way, such as power-supply cord or plug is damaged, liquid has been spilled or objects have fallen into the apparatus, the apparatus has been exposed to rain or moisture, does not operate normally, or has been dropped.
- Use only with a cart, stand, tripod, bracket, or table specified by the manufacturer, or sold with the apparatus. When a cart is used, use caution when moving the cart/apparatus combination to avoid injury from tip-over.



FCC Warnings

Warning: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- · Reorient or relocate the receiving antenna.
- · Increase the separation between the equipment and receiver.
- · Connect the equipment into an outlet on a circuit different
- from that to which the receiver is connected.Consult the dealer or an experienced radio/TV technician for help.

FCC Radiation Exposure Statement

This equipment complied with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator & your body.

Additional Warnings and Precautions

- CAUTION: TO PREVENT ELECTRIC SHOCK, MATCH WIDE BLADE OF PLUG TO WIDE SLOT, FULLY INSERT.
- Mains plug is used as disconnect device and it should remain readily operable during intended use. In order to disconnect the apparatus from the mains completely, the mains plug should be disconnected form the mains socket outlet completely.
- · WARNING: Shock hazard Do Not Open.
- Caution and marking information is located at the rear or bottom of the apparatus.
- WARNING: To reduce the risk of fire or electric shock, do not expose this apparatus to rain, moisture, dripping, or splashing.
- Objects filled with liquids, such as vases, shall not be placed on the apparatus.
- CAUTION: Use of controls or adjustments or performance of procedures other than those specified may result in hazardous radiation exposure.
- WARNING: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment
- WARNING: Do not place this unit directly onto furniture surfaces with any type of soft, porous, or sensitive finish. As with any rubber compound made with oils, the feet could cause marks or staining where the feet reside. We recommend using a protective barrier such as a cloth or a piece of glass between the unit and the surface to reduce the risk of damage and/or staining.
- WARNING: Use of this unit near fluorescent lighting may cause interference regarding use of the remote. If the unit is displaying erratic behavior move away from any fluorescent lighting, as it may be the cause.

- CAUTION: Danger of explosion if battery is incorrectly replaced. Replace only with the same or equivalent type.
- Battery shall not be exposed to excessive heat such as sunshine, fire or the like.
- Keep new and used batteries away from children. If the battery compartment does not close securely, stop using the product and keep it away from children.
- If you think batteries might have been swallowed or placed inside any part of the body, seek immediate medical attention.
- · Do not mix old and new batteries
- Completely replace all old batteries with new ones.
- Do not mix alkaline, standard (carbon-zinc), or rechargeable (ni-cad, ni-mh, etc) batteries.
- Batteries should be recycled or disposed of as per state and local guidelines.

FCC STATEMENT :

The service complian with Part 18 of the FCC Rules. Operation is subject to the following free conditions:

(1) 7his device may not been harmful adorterence, and

(2) The device must accept any interference reserved, including combinence that may taken without approximit.

Warning: Cronges or modifications roll examinity approved by the pilots insponsible for compliance could visit frequency authority to operate the equipment.

NOTE: This equipment has been balled and found to camply with the limits for a Clave 3. Signal boots, pursuant to Part 16 of the FCC Hales. These limits are designed to possible reasonable production against factorial for FCC Hales. These limits are designed to possible reasonable production against factorial factorial to a realisticital included. This reasonable production against factorial could be food-ency energy and 3 real statebol end and its accentions with the instruction, may been any energy with 7 rel instruction commandation. However, there is a guarantee that thereful methods to observe to observe reasonable interactions. The engineering could be the statebol and the food on a possible commandation. The engineering could be the statebol and the food on the or taken reasonable of to by to correct the billeterace by food in recent of the following measure.

Fischeré or relocatio the receiving artemes.

Exercises at the began allots between the angain ment and moniver.

Connect the upgement and an pullet on a calcul different from that to which the treatments terminated.

Consult the dealer or an experienced radio/Tv technician for help.

FGC Radiation Exposure Statement:

This equipment complets with FCC totilation exposure limits and forth for an uncomposited environment. This equipment should be installed and operated with minimum distance 20th between the radiator & your body.

Table of Contents

Setup

Features & Specifications - 5 Power - 5 Source Mode Indicator LED - 5 Includes - 5

Orientation

Rear View - 6 Speaker Inputs Detail (Rear) - 6 Speaker Controls (Top) - 6

Remote

Functions & Controls - 7

Bluetooth Wireless

Remote Learning

What Is the Learn Feature? - 9 Why Use the Learn Feature? - 9 Using the Learn Feature - 9

Audio Inputs

Optical Input - 10 Stereo RCA Inputs (Aux In) - 10 Line In - 10

Company Information

Contact Information - 12 International Support - 12 Warranty - 12

Setup

Features & Specifications

- 37" length
- Supports Bluetooth: range 60 ft.
- 2 channel stereo sound
- Digital volume control
- Full-function remote
- Optical audio input
- Aux In (3.5mm audio input)
- RCA stereo audio inputs

Power

the speaker and a standard wall outlet.

Includes

- · Remote control with 1 CR2025 battery pre-installed
- Optical audio cable
- AC/DC power adapter
- · Wall-mount hardware and instructions





Source Mode Indicator LED

STATUS	INDICATOR
Power Off	Red Light
Line In Mode	Green Light
Optical Mode	Amber Light
RCA/Aux In Mode	White Light
Bluetooth Pairing	Flashing Blue Light
Bluetooth Connected	Blue Light

Orientation

Rear View



Speaker Inputs Detail (Rear)



Speaker Controls (Top)



Power/Source

Press to power the unit ON or OFF. Press to switch audio source to Bluetooth, Optical, Aux In, or Line In modes. Volume

Press to adjust volume.

Pair/Play/Pause/Learn Press and hold to begin pairing to a Bluetooth device.

Press to play or pause audio (BLUETOOTH MODE).

With the unit powered OFF, press to begin using the learn function.

Remote

Functions & Controls



Remote Batteries

Requires 1 CR2025 battery (pre-installed).



Bluetooth Wireless

Pairing a Bluetooth Device for the First Time

- 1. When first powered on the sound bar defaults to Bluetooth mode. A voice will say, "Bluetooth", and the LED indicator will slowly flash blue. When pairing, remain within 3 feet of the Bluetooth device.
- 2. Using the controls on your Bluetooth device, select **ITB259** in the Bluetooth Settings to pair. If need be, refer to the user's manual for your specific device for more information.
- 3. When successfully paired, a voice will announce, "Bluetooth is connected", and the LED indicator will turn solid blue. Audio from the connected Bluetooth device will now be heard through the speaker.
- 4. Use the controls on the connected Bluetooth device to select and play audio. Use the speaker controls or the connected Bluetooth device to play, pause, and adjust the volume level.
- 5. After initial pairing, whenever the sound bar is powered on, the sound bar will automatically connect to the last Bluetooth device used. Note: If your device should become unpaired or you find it is unable to connect, press & hold the Play button on remote or press the Pair/Learn button on the soundbar to enter pairing mode. A voice will announce, "Bluetooth is connecting", and you can connect to the speaker manually.

Playing Audio Wirelessly

- 1. After pairing to a Bluetooth device, use the controls on the connected Bluetooth Device to select a track.
- 2. Play, pause or skip a selected track using the controls on the connected Bluetooth Device or the soundbar's remote.
- 3. Audio played through the connected Bluetooth device will now be heard through the speakers.

Party Plus Mode

If you have another ITB259 soundbar, you can pair and play the two together for a surround sound effect, or have two playing in different rooms.

- 1. To enter Party Plus Mode, please make sure the unit is in Bluetooth mode. Quickly press the **Pair/Learn** button twice on one of the soundbars..
- 2. When the two soundbars are paired together a voice will announce the connection.
- Connect your Bluetooth device to the bars using the steps from the "Pairing a Bluetooth Device for the First Time" section above.
- 4. Use your device to select and play tracks. The audio will now be heard through both soundbars.
- 5. To disconnect the soundbars, quickly press the Pair/Learn button twice.

Note: To use Party Plus Mode, please make sure that you connect the soundbars before pairing to your Bluetooth device. You will not be able to connect the two soundbars if you are already paired to a Bluetooth device.

Remote Learning

What Is the Learn Feature?

The Learn feature captures remote commands from your television remote, and teaches your soundbar to operate when these commands are pressed. Power, volume and mute are a few examples of commands that the bar speaker can learn.

Why Use the Learn Feature?

Teaching the bar speaker remote commands will reduce the number of remotes needed, save time searching for remote codes, and improve the ease of operation.

Note: Not all functions of the sound bar will be available through your own remote control, such as bass and treble. Use the included remote for these functions. While your ITB259 sound bar is able to learn most IR protocols, not all can be programmed.

Using the Learn Feature

- 1. With the power Off, press the Learn button on the unit. An indicator will flicker red.
- 2. Press the button you desire to be learned on the included remote. *For example: Volume* +
- 3. The red light will continue to flicker, and another indicator will display a blue light.
- 4. Press the corresponding button on your remote.
- 5. The red light will continue to flicker, and another indicator will display a green light.
- 6. When the green light turns off, the button command is saved.
- The programmed button on your remote will now be able to control your sound bar. Note: It is necessary to program each button i.e. channel and volume + and - separately.
- 8. To start over, press and hold the **Learn/Pair** button for 5 seconds. If the sound bar has failed to learn a command, the LED indicator will display an orange light. Please try again with a different remote

Audio Inputs

Optical Input

Requires an audio source with an Optical Audio Output and a Digital Optical Audio Cable (included).

- 1. Using a Digital Optical Audio Cable, connect the **Optical Input** on the sound bar to the Optical Output on your audio source (TV, amplifier, etc.).
- 2. Power ON the sound bar and press **Optical** on the remote or **Source** on the sound bar to select **Optical Mode.** A voice will announce the source mode and the indicator will turn orange.
- 3. On the connected audio source (TV, amplifier, etc.), be sure the audio settings are set to PCM or Optical Audio.
- 4. Audio played through the connected audio source (TV, amplifier, etc.) should now be heard through the speaker.

Important tips for optical audio:

- Use the correct optical audio cable and make sure that it is firmly seated in both source and sound bar sockets.
- Optical audio output is activated from the audio source (a red light should be visible from the optical socket). It may be labeled SPDIF in the settings menu of the source.
- The optical output source should be set to output PCM and not Dolby Digital.

Stereo RCA Inputs (Aux In)

Requires RCA stereo audio cable (not included). When connecting RCA stereo audio plugs (Red/White), match them to their corresponding color coded ports.

- 1. Connect an RCA stereo audio cable to the **Aux In** ports on the sound bar and the RCA audio outputs on a television or other audio source.
- 2. Power ON the sound bar and press **Source** on the sound bar or **Aux In** on the remote to select **Aux In Mode.** A voice will announce the source mode and the indicator will turn white for Aux In.
- 3. Audio played through the television or other source should now be heard through the speakers.

Line In

Requires a 3.5mm audio cable (not included).

- 1. Connect a 3.5mm audio cable to the Line In on the unit and the audio output/headphone jack on an audio device.
- 2. Power ON the sound bar and press **Source** on the sound bar or **Line In** on the remote to select **Line In Mode.** A voice will announce the source mode and the indicator will turn green.
- 3. Use the controls on the connected device to select and play audio. Be sure the volume on your connected device is audible when you begin playing.

Optical Input - Detail



 Please remove the protective plastic cap over the end of the optical cable before attempting to connect it.

Stereo RCA Inputs (Aux In) - Detail



Line In - Detail



Company Information

Contact Information

Website: www.iLiveElectronics.com Email Support: prodinfo@dpiinc.com Email Parts: partsinfo@dpiinc.com Phone Support: 1-888-999-4215

Warranty

For Warranty Information and the most up-to-date version of this User's Guide, go to: **www.iLiveElectronics.com**

International Support

To download this User's Guide in English, Spanish, and French, or to get answers to frequently asked questions, visit the support section at: **www.iLiveElectronics.com**

Para descargar este Manual del Usuario en inglés, español y francés, o para obtener respuestas a preguntas frecuentes, visite la sección de apoyo en: **www.iLiveElectronics.com**

Pour télécharger ce guide de l'utilisateur en anglais, espagnol ou français, ou pour obtenir des réponses à des questions fréquemment posées, consultez la rubrique d'assistance sur: www.iLiveElectronics.com



Copyright © 2022 Digital Products International (DPI, Inc.) All other trademarks appearing herein are the property of their respective owners. Specifications are subject to change without notice.