



NATURE POWER 750 WATT POWER INVERTER



Cable with 12V car plug
16AWG, 1x21"

Cable with battery clamps
8AWG, 2x23"



Features

Convert battery power to household AC power installation.

- 2 x AC Outlets Allow You to Run Multiple Devices at The Same Time
- Runs Home Appliance, TVs , Power Tools and More
- Comes With Both DC Plug and Battery Clamps
- 750 Watt Continuous Output, 1500 Watts Surge
- Compact Size



SPECIFICATIONS

AC OUTPUT

Power (Continuous): 750W

Power (Peak): 1500W

Voltage: 115±10 Vac

Frequency: 60±3

Waveform: Modified sinewave

AC Outlet: 2 x 3Prong AC outlet

DC OUTPUT

USB: 1 x 5V/2A

DC INPUT

Voltage (nominal): 12.8-13.2Vdc

Operation Range: 10.0-15.0Vdc

Material: ABS, Stell, Aluminum

PROTECTION:

Input Undervoltage Shutdown/Warning: 10.0±0.5Vdc

Input Undervoltage Recovery: 12.0±0.5Vdc

Input Overvoltage Shutdown: 15.5±0.5Vdc

Overload Shutdown: Yes

Output Short circuit Protection: Yes

Over Temperature Shutdown: Yes

SHIPPING DETAILS

Item Number: 37750

UPC Code: 839290003312

Country of Origin: China / Taiwan

Product Dimensions: 9.7 x 4.2 x 2.2 in

Color box Dimensions: 10.18 x 6.24 x 2.42 in

Product Weight: 3 lbs with package

2.7 lbs without package

Master Quantity: -

Master Dimensions: - in

Master Weight: - lbs



1-800-588-0590

www.naturepowerproducts.com



fb.me/NaturePowerProducts

