

One-Light LED Flush Mount

 Ceiling mounted • Damp location listed **PROGRESS LED**


P350020-020-30

Description:

One-light 11-3/8 inch Square LED Flush Mount featuring a square Alabaster glass bowl in an Antique Bronze finish. Fixtures are dimmable to 10 percent with Triac or ELV dimmers. 3000K and 90CRI.

Specifications:

- Antique Bronze (-020) (painted)
- Steel Construction
- Etched Alabaster glass diffuser
- LED Module is replaceable (part # 93074252;)
- 3000K color temperature, 90+ CRI
- TM-21 60,000 hour life.
- 2015 lumens 80 lumens/watt (source).
- Dimmable to 10% brightness (See Dimming Notes)
- Unit covers a standard 4" octagonal recessed outlet box
- Mounting strap for outlet box included
- 6" of wire supplied
- ENERGY STAR® qualified
- Meets California Title 24 JA8-2016

Performance:

Number of Modules	1
Input Power	25w
Input Voltage	120 V
Input Frequency	60 Hz
Lumens/LPW (Source)	2015/80 (LM-82)
Lumens/LPW (Delivered)	1302/52.9 (LM-79)
CCT	3000 K
CRI	90+
Life (hours)	60,000 (L70/TM-21)
FCC	Meets FCC Title 47, Part 15 Class B
Min. Start Temp	-30 °C
Max. Operating Temp	30 °C
Warranty	5 year warranty
Labels	cCSAus Damp location listed ENERGY STAR® qualified Meets California Title 24 JA8-2016

Images:



Dimensions:

Square: 11-3/8"
Height: 5"

Glass
Width: 11-3/8"
Length: 11-3/8"
Height: 4-1/2"

P350020-020-30**Dimming Notes:**

P350020 is designed to be compatible with many Triac/Forward Phase or ELV/Reverse Phase controls.

The following is a partial list of known compatible dimmer controls.

Dimming Controls

Lutron Diva DVELV-300P

Lutron Nova T NTELV-300

Lutron Caseta

Lutron Ariadni AY-600P

Lutron Lumea LG-603PG

Leviton SureSlide 6672

Leviton SureSlide 6674

Lutron Ariadni AYCL-153P

Lutron Skylark Contour CTCL-153P

Lutron Diva DVCL-153P

Cooper Devine AL DAL06P

Lutron Maestro MACL-153M

Lutron Ariadni AYL-600P

Lutron Maestro MA-600

Lutron NOVA T NTLV-600

lutron Maestro MAELV-600

Lutron spacer/system SPSELV-600

Lutron Nova N-600

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation.

Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.