



# XP10000HX

DUAL FUEL PORTABLE GENERATOR

10,000 STARTING WATTS • 8,000 RUNNING WATTS



FEATURING CO ALERT TECHNOLOGY





# XP10000HX

DUAL FUEL PORTABLE GENERATOR


## FEATURES

- Large Fuel Tank
- All Metal Construction
- Powerful OHV Engine
- All-Copper Windings
- Digital Command Center
- Fully-Loaded Power Panel
- Push Button Start
- Low Oil Sensor



CO ALERT TECHNOLOGY

## OUTLETS



**X4**

120V 20A  
GFCI Outlet



**X1**

120V 30A  
Twist Lock



**X1**

120/240V 30A  
Twist Lock



**X1**

120/240V 50A  
Heavy Duty Outlet

## SPECS

<b>Watts (Gasoline)</b>	10,000 (peak) • 8,000 (running)
<b>Watts (Propane)</b>	9,500 (peak) • 7,600 (running)
<b>Engine</b>	OHV 439cc
<b>Amperage</b>	66.67A / 33.33A
<b>Voltage</b>	120V / 240VAC
<b>Fuel Type</b>	Gasoline / Propane
<b>Runtime (Gasoline) at 50% Load</b>	10.4 hrs
<b>Runtime (Propane) at 50% Load</b>	8.6 hrs