

Nest Wifi Pro (Wi-Fi 6E)
Technical Specifications
2022

Google Nest Wifi Pro (Wi-Fi 6E) Tech Specs

Spec Category	Google Nest Wifi Pro (Wi-Fi 6E)		
Coverage ¹	[US] Up to 2200 square feet per router Router 1-pack: Up to 2200 square feet of coverage Router 2-pack: Up to 4400 square feet of coverage Router 3-pack: Up to 6600 square feet of coverage Router 4-pack: Up to 8800 square feet of coverage Router 1-pack: Up to 200 square meters of coverage Router 1-pack: Up to 200 square meters of coverage Router 3-pack: Up to 600 square meters of coverage Router 1-pack: Up to 120 square meters of coverage Router 2-pack: Up to 120 square meters of coverage Router 3-pack: Up to 220 square meters of coverage Router 3-pack: Up to 320 square meters of coverage Router 3-pack: Up to 320 square meters of coverage Router 3-pack: Up to 320 square meters of coverage Expandable IEEE 802.11s mesh Wi-Fi Scalable and flexible system – add routers for more coverage		
Automatic Wi-Fi optimization	 Proactive band steering directs your devices to radio channels with the best performance Proactive 802.11k/v client steering enables seamless mesh point roaming for uninterrupted Wi-Fi Auto-QoS for video calls and Stadia gaming Device prioritization, up to 8 hours Self-monitors and diagnoses network issues 		
Smart home connectivity	 Thread border router built in Matter² (coming soon) Bluetooth® Low Energy (BLE) Designed to support higher-power 6 GHz channels, when available (AFC-ready) 		

¹Router placement and home size, materials and layout can affect how Wi-Fi signal travels. Poor placement and larger homes or homes with thicker walls or long, narrow layouts may need extra Wifi points for full coverage. Strength and speed of signal will also depend on your internet provider. More than 5 routers in a network may result in degraded performance and is not recommended. ²Check g.co/nest/matternow for availability of Matter's functionality on Nest Wifi Pro.

Performance	. Wi-Ei 4E 902 11av Wi-Ei standard			
Performance	 Wi-Fi 6E, 802.11ax Wi-Fi standard Wi-Fi 6E is up to 2x faster than Wi-Fi 6³ 			
	• WI-FI of is up to 2x faster than WI-FI of • [US only] AXE5400 – combined speeds up to 5.4 Gbps ⁴			
	• [Outside of US] AXE4200 – combined speeds up to 4.2			
	Gbps ⁴			
	o 2x2 (6 GHz)			
	o 2x2 (5 GHz)			
	o 2x2 (2.4 GHz)			
	Can handle up to 100 connected devices per point (up to 300)			
	devices in a 3-pack network) ⁵			
	4K video streams in coverage area ⁶			
	Dual-core 64-bit ARM CPU			
	• 1GB RAM, 4GB flash			
Security built in	WPA3 encryption			
and the second s	Secure booting and software updates help protect Nest Wifi			
	Pro from running unauthorized software and router hacks			
	Automatic security and software updates. [For EU countries:			
	replace this bullet with "Legally required software and security			
	updates will be provided. See here for more."]			
	Family protections, including parental controls			
	Manage devices connected to your network			
	Create separate guest network access			
Ports and	Two Ethernet ports support 1 Gbps wired speeds per router			
connectors				
Power	• 22.5 W (10 V/2.25 A)			
Colors	• [US] Snow, Fog, Linen, Lemongrass			
	• [CA / AU / NZ] Snow, Fog			
	• [ROW] Snow			
Dimensions and	• 130 mm height			
weight	• 117 mm width			
	85 mm depth			
	450 g weight			
Sustainability	Nest Wifi Pro (Wi-Fi 6E) is made with approximately 60%			
,	recycled materials based on product weight.			
Compatibility	Nest Wifi Pro (Wi-Fi 6E) cannot be combined in a mesh			
- Janipationity	network with previous-generation Nest Wifi or Google Wifi			
routers or points				
	'			

³Up to 2x faster as compared to a Wi-Fi 6 router that supports 80 MHz channels. Wi-Fi 6E specifications are based on use of a Wi-Fi 6 or later generation client device that supports 160 MHz channels. Actual speeds depend on your internet service provider, network conditions, connected device, local regulations and environmental factors.

⁴ Combined speeds are total speeds across all bands, and are derived from IEEE Standard 802.11 specifications based on use of Wi-Fi 6 or later generation connected devices that support 160 MHz channels. Actual speeds will depend on your internet service provider, network conditions, connected device, local regulations and environmental factors.

This is based on only using connected devices at a maximum data rate of 1Mbps. Requires sufficient broadband internet

connection and connected devices must be located within Wi-Fi coverage area described at g.co/nestwifi/coverage. Strength and speed of signal will also depend on your internet provider.

⁶4K-capable device and content, and sufficient internet speeds are required.

Languages	English, Danish, Dutch, Finnish, French, German, Italian, Japanese, Norwegian, Portuguese, Spanish, Swedish
Warranty	 [US, CA, JP] 1-year limited warranty (details in box). For help, visit g.co/devicewarranty. [GB, EU, AU, NZ] 2-year limited warranty (details in box). For help, visit g.co/devicewarranty.

What's included in the box - U.S.

Nest Wifi Pro (Wi-Fi 6E) 1-pack	Nest Wifi Pro (Wi-Fi 6E) 2-pack	Nest Wifi Pro (Wi-Fi 6E) 3-pack	Nest Wifi Pro (Wi-Fi 6E) 4-pack [Costco only]
• Router	• 2 routers	• 3 routers	• 4 routers
• 22 W power adapter	• 2 power adapters (22 W)	• 3 power adapters (22 W)	• 4 power adapters (22 W)
• Ethernet cable (6.5 ft)			
Quick start guide	Quick start guide	Quick start guide	Quick start guide
Safety & Warranty guide			

Requirements - U.S.

- Nest Wifi Pro requires a modem, active internet connection, available Ethernet port, nearby electrical outlet(s), Google Account, the Google Home app, and compatible phone (OS requirements at g.co/nestwifi/req).
- All features, functionality, and other product specifications may change without notice or obligation.
- © Google LLC. Google, Google Nest Wifi Pro, Google Home, G logo, and related marks and logos are trademarks of Google LLC.