

## INVERTER GENERATOR





POWERING YOUR life.

#> Model 201323

UPC **817198027043** 


∑★ Warranty 3 Years



1850
RUNNING WATTS
Propane: 1665















## Receptacles







**15.4 AMP** 120V, 5-20R

Recoil



CARBON MONOXIDE AUTO-SHUTOFF SYSTEM









## Q Specifications

START TYPE

VOLTAGE (V) AC	120
VOLTMETER	Intelligauge
ENGINE SIZE (cc)	80
FUEL TYPE	Gasoline or Propane
GASOLINE CAPACITY (gal.)	1.05
OIL TYPE	10W-30
OIL CAPACITY (fl. oz./mL)	13.5/400
LOW OIL SHUT-OFF	Yes
EMISSIONS	EPA III

Our 2500-watt inverter is one of the lightest in the industry and features CO Shield® carbon monoxide auto shutoff system. The Dual Fuel feature allows the 80cc engine to run on gasoline or propane. Enjoy the quiet 53 dBA for up to 11.5 hours on gasoline or up to 25 hours with a 20-lb propane tank and increase your power with the optional Parallel Kit.

## Inside the box

**OIL FUNNEL** 

**ENGINE OIL** 

GENERATOR
PROPANE HOSE 2.3 FT.
OPERATOR'S MANUAL

What You Need

**GASOLINE OR PROPANE** 

(!) \*Specifications, descriptions and illustrations are subject to change without notice.



