

# FEATURES & SPECIFICATIONS

# INTENDED USE

Provides general illumination in residential and light commercial applications. Ideal for use in workshops, utility rooms, and garages.

#### CONSTRUCTION

The steel Wire Guard helps provide protection to the fixture bulb area. Includes a 5' power cord, 5A Max. convenience outlet and a pull chain power switch. The residential electronic ballast (120V 60Hz1.50 Amps) starts reliably down to 0°F For use on non-dimmable switches only.

### ELECTRICAL

Utilizes (4) 32W linear T8 fluorescent lamps (not included).

# INSTALLATION

Fully assembled, ready to install. Chain mount to ceiling using the  $12^{\prime\prime}$  mounting chains. All mounting hardware is included.

#### LISTINGS

cUL Listed to US and Canadian safety standards.

## WARRANTY

1-year limited warranty. Complete warranty terms located at: <u>www.acuitybrands.com/CustomerResources/Terms\_and\_conditions.aspx</u>

**NOTE:** Actual performance may differ as a result of end-user environment and application. Specifications subject to change without notice.

Specifications	w		
Length: 48 (121.9)			
Width: 12 (30.5)			
Height: 4 (10.2)		L —	
	Н		

All dimensions are inches (centimeters) unless otherwise indicated.

Catalog Number
Notes
Гуре

**Indoor General Purpose** 



ORDERING INFORMATION	b
UKUEKINGINFUKMAIIUN	

# Example: 1284GRD RE

1284GRD		RE	
Series		Ballast/voltage	
1284GRD	Requires (4) T8 fluorescent lamps (not included)	RE	120V residential electronic ballast

🧶 LITHONIA LIGHTING